

FATIGUE STRENGTH REDUCTION MODEL:
RANDOM3 and RANDOM4 USER MANUAL

Lewis
Grant
NW-39-CR
200667
803

Prepared by :

Lola Boyce, Ph.D., P.E.
Thomas B. Lovelace

APPENDIX 2
of Annual Report
of Project Entitled
Development of Advanced Methodologies
for Probabilistic Constitutive Relationships
of Material Strength Models

NASA Grant No. NAG 3-867

Prepared for :

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION
Lewis Research Center
Cleveland, OH 44135

(NASA-CR-184940) FATIGUE STRENGTH REDUCTION
ECDL: RANDOM3 AND RANDOM4 USER MANUAL,
APPENDIX 2 Annual Report (Texas Univ.)
80 p

N89-23891

CSCL 20K

G3/39 Unclas
0200667

The Division of Engineering
The University of Texas at San Antonio
San Antonio, TX 78285
January, 1989

**FATIGUE STRENGTH REDUCTION MODEL:
RANDOM3 and RANDOM4 USER MANUAL**

Prepared by :

**Lola Boyce, Ph.D., P.E.
Thomas B. Lovelace**

**APPENDIX 2
of Annual Report
of Project Entitled
Development of Advanced Methodologies
for Probabilistic Constitutive Relationships
of Material Strength Models**

NASA Grant No. NAG 3-867

Prepared for :

**NATIONAL AERONAUTICS AND SPACE ADMINISTRATION
Lewis Research Center
Cleveland, OH 44135**

**The Division of Engineering
The University of Texas at San Antonio
San Antonio, TX 78285
January, 1989**

TABLE OF CONTENTS

| SECTION | PAGE |
|---|------|
| 1.0 Introduction | 1 |
| 2.0 Theoretical Background | 2 |
| 3.0 Input Data | 4 |
| 4.0 Sample Problem | 7 |
| 5.0 References | 11 |
| 6.0 Appendix A: Physical Quantities, Symbols, and Units | 12 |
| 7.0 Appendix B: RANDOM3 Sample Problem: Source, Input and Output Files .. | 13 |
| 8.0 Appendix C: RANDOM4 Sample Problem Source, Input and Output Files .. | 37 |
| 9.0 Appendix D: IMSL Subroutine Calls from RANDOM3 and RANDOM4 | 76 |
| 10.0 Appendix E: SAS/GRAPH Program for RANDOM3 and RANDOM4 | 77 |

1.0 INTRODUCTION

This User Manual documents the FORTRAN programs RANDOM3 and RANDOM4. They are based on fatigue strength reduction, using a probabilistic constitutive model. They predict the random lifetime of an engine component to reach a given fatigue strength (see Section 2.0, Theoretical Background).

Included in this Manual are details regarding the theoretical backgrounds of RANDOM3 and RANDOM4, input data instructions and sample problems illustrating the use of RANDOM3 and RANDOM4 . Appendix A gives information on the physical quantities, their symbols, FORTRAN names and both SI and U.S. Customary units. Appendix B and C include photocopies of the actual computer printout corresponding to the sample problems. Appendices D and E detail the IMSL, Version 10¹, subroutines and functions called by RANDOM3 and RANDOM4 and SAS/GRAFH² programs that can be used to plot both the probability density functions (p.d.f.) and the cumulative distribution functions (c.d.f.).

2.0 THEORETICAL BACKGROUND

Fatigue strength data are usually presented as cycles to failure for each of several stress amplitudes, the familiar S-N diagram. Results indicate that for lower stress amplitudes the cycles (or time) to failure increases. Thus, a power curve fit through the data yields a monotonically decreasing curve. In general, this curve is represented as

$$S = [N/C']^{-1/m'} \quad (6)$$

where the primitive variables in this equation are as follows: S is the applied constant amplitude alternating stress at failure or fatigue strength, N is number of cycles, C' is a material parameter that varies from specimen to specimen and m' is a material constant.³ Equation (6) can be written in terms of "cycles to reach a given fatigue strength" as

$$N = C' S^{-m'} \quad (7)$$

Recently another fatigue strength reduction model has been proposed that takes into account the effect of temperature as well as other parameters that affect strength.⁴ The general form of the constitutive relationships for this model is applied to the constituents of high temperature composite materials. Specifically, it is applied herein for the case of a single material constituent. The mechanical property of interest is fatigue strength which is expressed in terms of primitive variables, including the general categories of temperature, mechanical cycles and mean stress. For these categories, the relationship becomes

$$\frac{S}{S_0} = \left[\frac{T_F - T}{T_F - T_0} \right]^n \left[\frac{S_F - \sigma}{S_F - \sigma_0} \right]^m \left[\frac{\log N_{MF} - \log N_M}{\log N_{MF} - \log N_{MO}} \right]^q \quad (8)$$

where S is the applied constant amplitude alternating stress at failure (fatigue strength) at current (or operating) temperature, T , mean stress, σ , and mechanical cycle, N_M . S_0 is fatigue strength at reference temperature, T_0 (usually room temperature), reference mean stress (or residual stress), σ_0 , and reference mechanical cycle, N_{MO} . Also, T_F is the final or melting temperature of the material, S_F is the final or tensile strength of the material, and N_{MF} is the final mechanical cycle or lifetime. Empirical parameters, n , m , and q , are determined from available experimental data or estimated from anticipated behavior of the particular product term.⁵ Note that the term containing mechanical cycles is expressed in terms of the log of cycles rather than cycles. This formulation is attractive when N_M and N_{MO} are small compared to N_{MF} . The equation may be solved for N_M , or the "cycles to reach a given fatigue strength." The expression is

$$N = 10 \exp \left[\log N_{MF} - \left[(\log N_{MF} - \log N_{MO}) \left[\frac{S}{S_0 \left[\frac{T_F - T}{T_F - T_0} \right]^n \left[\frac{S_F - \sigma}{S_F - \sigma_0} \right]^m} \right]^{1/q} \right] \right] \quad (9)$$

For values typical of a cast nickel base-superalloy subjected to typical loads and temperatures, equation (9) indicates increasing life for decreasing temperature, decreasing tensile mean stress, and decreasing applied alternating stress. It indicates decreasing life for increasing temperature, decreasing compressive mean stress, and increasing applied alternating stress. Therefore, equation (9) predicts observed trends in general.

Probabilistic analysis, via simulation, yields the distribution of the dependent random variable, cycles, N . A probability density function (p.d.f.) of cycles is generated using the maximum penalized likelihood method for RANDOM3. For RANDOM4, a p.d.f. of cycles is generated using the maximum entropy method. Maximum entropy uses Jaynes' principle which says that "the minimally prejudiced distribution is that which maximizes the entropy subjected to the constraints supplied by the given information."⁶

3.0 INPUT DATA

Data input for RANDOM3 and RANDOM4 is user friendly and easy to manipulate (see, for example, the file entitled NORMAL.INP, in Section 4.0). The first twelve lines of input have the same format, 2E12.4 and the last two lines differ. The last two lines of input have the formats I3,2X,I3,2X,2E12.4,2X,I3 and I3, respectively. A brief, line by line description is given along with an example for each line (NOTE: the ruler is to aid the user in formatting and is not a part of the input). A table listing the physical quantities, their units and symbols is given in Appendix A.

1. Random Number Generator Seed, ISEED, and Sample Size, NTOT

EXAMPLE:

123456789012345678901234567890
1 40

2. Ultimate Tensile Strength, SF

EXAMPLE:

123456789012345678901234567890
900.0000 45.0000

3. Log of Final Cycle, NMF

EXAMPLE:

123456789012345678901234567890
8.0000 0.8000

4. Reference Fatigue Strength, SO

EXAMPLE:

123456789012345678901234567890
500.0000 25.0000

5. Log of Reference Cycle, NMO

EXAMPLE:

123456789012345678901234567890
7.0000 0.7000

6. Current Fatigue Strength, S

EXAMPLE:

123456789012345678901234567890
250.0000 12.0000

7. Residual Compressive Stress, SIGO

EXAMPLE:

123456789012345678901234567890
20.0000 1.0000

8. Current Mean Stress, SIG

EXAMPLE:

123456789012345678901234567890
150.0000 7.5000

9. Temperature Exponent, XXN, Stress Exponent, XXM, and Cycle Exponent, XXQ

EXAMPLE:

123456789012345678901234567890
0.5000 0.0150

10. Melting Temperature, TF

EXAMPLE:

123456789012345678901234567890
1500.0000 75.0000

11. Reference Temperature, TO

EXAMPLE:

123456789012345678901234567890
20.0000 0.6000

12. Current Temperature, T

EXAMPLE:

123456789012345678901234567890
850.0000 25.0000

13. The DESPL¹ parameters are NODE, INIT, ALPHA, EPS, and MAXIT and are entered in that order as follows:

EXAMPLE:

1234567890123456789012345678901234567890
21 0 20.0000 1.0E-05 30

14. The DESPL parameter, IOPT, is entered as follows:

EXAMPLE:

1234567890
2

4.0 SAMPLE PROBLEMS FOR RANDOM3 AND RANDOM4

The objective of these programs is to predict the random lifetime to reach a given fatigue strength for an engine component. The theory is based on fatigue strength reduction, using a probabilistic constitutive model. The only difference between RANDOM3 and RANDOM4 is the method used to generate p.d.f. estimates. RANDOM3 uses maximum penalized likelihood, while RANDOM4 uses maximum entropy (see Section 2.0, Theoretical Background). RANDOM3 and RANDOM4 input parameters are given in Table A2.1.

TABLE A2.1 RANDOM3 and RANDOM4 input (SI units)

| FORTRAN Name | Distribution Type | Mean | Standard Deviation (Value) | Deviation (% of Mean) |
|--------------|-------------------|--------|----------------------------|-----------------------|
| SF | normal | 900.0 | 45.0 | (3%) |
| NMF | lognormal | 8.0 | 0.8 | (10%) |
| SO | lognormal | 500.0 | 25.0 | (5%) |
| NMO | lognormal | 7.0 | 0.7 | (10%) |
| S | lognormal | 250.0 | 12.5 | (5%) |
| SIGO | lognormal | -20.0 | -1.0 | (1%) |
| SIG | lognormal | 150.0 | 7.5 | (5%) |
| XXN | normal | 0.5 | 0.015 | (0.3%) |
| XXM | normal | 0.5 | 0.015 | (0.3%) |
| XXQ | normal | 0.5 | 0.015 | (0.3%) |
| TF | normal | 1500.0 | 45.0 | (3%) |
| TO | normal | 20.0 | 0.6 | (3%) |
| T | normal | 850.0 | 25.5 | (3%) |

The input is entered in the following format in a file entitled NORMAL.INP.

| |
|--|
| 1234567890123456789012345678901234567890 |
| 1 40 |
| 900.0000 45.0000 |
| 8.0000 0.8000 |
| 500.0000 25.0000 |
| 7.0000 0.7000 |
| 250.0000 12.5000 |
| 20.0000 1.0000 |
| 150.0000 7.5000 |
| 0.5000 0.0150 |
| 1500.0000 75.0000 |
| 20.0000 0.6000 |
| 850.0000 25.5000 |
| 21 0 20.00 1.0E-05 30 |
| 2 |

Execution of RANDOM3 and RANDOM4 (source code entitled NR3.FOR and NR4.FOR, respectively) produces files entitled RANDM33 and RANDM44. These give intermediate results (see Appendices B and C). Execution also produces plotfiles entitled PLOT1 and PLOT2 (see Appendices B and C). These files are used to plot the X and Y axes of the probability density function (p.d.f.) and the cumulative distribution function (c.d.f.), respectively, generated by RANDOM3 and RANDOM4. The plots are drawn from the plotfiles by the SAS/GRAFH graphing program (see Appendix D). These plots for the sample problem are shown Figures 1, 2, 3, and 4. This same sample problem has been reported in Boyce and Chamis.⁷ There, however, it utilized U.S. Customary units and older versions of RANDOM3 and RANDOM4 (using IMSL Version 9.2 subroutines).




Fig. A2.1 p.d.f. of log of mechanical cycles for fatigue strength reduction model, using maximum penalized likelihood method of p.d.f. generation.




Fig. A2.2 c.d.f. of log of mechanical cycles for fatigue strength reduction model, using maximum penalized likelihood method of p.d.f. generation.




Fig. A2.3 p.d.f. of log of mechanical cycles for fatigue strength reduction model, using maximum entropy method of p.d.f. generation.




Fig. A2.4 c.d.f. of log of mechanical cycles for fatigue strength reduction model, using maximum entropy method of p.d.f. generation.

5.0 REFERENCES

¹ IMSL, "STAT/LIBRARY, FORTRAN Subroutines for Statistical Analysis", Houston, Texas

² SAS Institute, Inc., SAS/GRAFH User's Guide, Version 5 Edition, Cary NC: SAS Institute, Inc., 1985, 596 pp.

³ Madsen, H.O., "Bayesian Fatigue Life Prediction," Probabilistic Methods in the Mechanics of Solids and Structures, S. Eddwertz and N.C. Lind, Eds., Proceedings of the IUTAM Symposium, Stockholm, Sweden, 1984, pp. 395-406.

⁴ Hopkins, D.A. and Chamis, C.C., "A Unique Set of Micromechanics Equations for High Temperature Metal Matrix Composites," NASA TM87154, Nov., 1985.

⁵ Chamis, C.C. and Hopkins, D.A., "Thermoviscoplastic Nonlinear Constitutive Relationships for Structural Analysis of High Temperature Metal Matrix Composites," NASA TM 87291, Nov., 1985.

⁶ Siddall, J.N., "A Comparison of Several Methods of Probabilistic Modeling," Proceedings of the Computers in Engineering Conference, ASME, San Diego, CA, Vol. 4, 1982, pp. 231-238.

⁷ Boyce, L. and Chamis, C.C., "Probabilistic Constitutive Relations for Cyclic Material Strength Models," Proceedings, 29th Structures, Structural Dynamics and Materials Conference, Williamsburg, VA, 1988.

6.0 APPENDIX A

PHYSICAL QUANTITIES, SYMBOLS, AND UNITS

The physical quantities, their symbols and units for the fatigue crack growth model are given in the following table.

Table A2.2 Physical quantities, symbols, and units for fatigue crack growth model for RANDOM3 and RANDOM4.

| Physical Quantity | Theory Symbol | FORTRAN Name | SI | Units | U.S. |
|-------------------------------|-----------------|--------------|-----|---------------|------|
| Ultimate Tensile Strength | SF | SF | MPa | ksi | |
| Final Cycle (lifetime) | N _{MF} | NMF | | dimensionless | |
| Reference Fatigue Strength | SO | SO | MPa | ksi | |
| Reference Cycles | N _{MO} | NMO | | dimensionless | |
| Current Fatigue Strengths | S | S | MPa | ksi | |
| Residual Compressive Stress | σ _o | SIGO | MPa | ksi | |
| Current Mean Stress | σ | SIG | MPa | ksi | |
| Empirical Material Parameters | n | XXN | | dimensionless | |
| | m | XXM | | dimensionless | |
| | q | XXQ | | dimensionless | |
| Melting Temperature | TF | TF | °C | °F | |
| Reference Temperature | TO | TO | °C | °F | |
| Current Temperature | T | T | °C | °F | |

7.0 APPENDIX B

RANDOM3 SAMPLE PROBLEM: SOURCE, INPUT AND OUTPUT FILES

ORIGINAL PAGE IS
OF POOR QUALITY

03200
03203
03202
03200
03201
03202
03203
03202

卷之三

卷之三

| | | | | | | | | | |
|--------|------|------|------|------|------|------|------|------|------|
| 000000 | CCCC | EEEE | FFFF | AAAA | BBBB | CCCC | FFFF | AAAA | BBBB |
| 000000 | CCCC | EEEE | FFFF | AAAA | BBBB | CCCC | FFFF | AAAA | BBBB |
| 000000 | CCCC | EEEE | FFFF | AAAA | BBBB | CCCC | FFFF | AAAA | BBBB |
| 000000 | CCCC | EEEE | FFFF | AAAA | BBBB | CCCC | FFFF | AAAA | BBBB |
| 000000 | CCCC | EEEE | FFFF | AAAA | BBBB | CCCC | FFFF | AAAA | BBBB |

File DUAO:[CNR3.FOR]3 (252,112,0) last revised on 22-DEC-1988 13:08, is a 48 block sequential file owned by UIC [DECNET]. The records are variable-length-with-implied-CR-carriage-control. The longest record is 72 bytes.

on Plaintiff LTA4; on 22-DEC-1988, 13:09, from queue TERNLAL20A, User defined accountname DECE1, User defined 1000, Startdate

BRIEFING PAPER

卷之三

14

```

JOB=M=SMBOYCE=9948530>R=F=30>HF=3000000>
JUCOUNT,PNU=10LAB,
DELETE,PDN=NR3BLD, ID=SMBOYCE,
DELT=7,LST,
REWIND,DN=1BLD,
SAVE,DN=1BLD, ID=SMBOYCE,
DELETE,PDN=NR3BLD, ID=SMBOYCE, ED=-1.

C RANDOM MICROMECHANICS CONSTITUTIVE EQUATIONS!
C AND APPLIED TO FATIGUE, INFLAT, NMISG, MAXIT, NODE
C INTEGER, NTOT, ISEED, M, INTL, NMISG, MAXIT, NODE
C REAL XM, YH, TS, EPS, P, RWKSP, / RWKSP /
C DIMENSION WORKNSP / RWKSP /
C DIMENSION XLNMF(10000),XLNMF(10000),S0(:0000),
C DIMENSION XLNHO(10000),SIG(10000),
C DIMENSION SIGO(10000),SIG(10000),
C DIMENSION XXNM(10000),XXM(10000),XXQ(10000),
C DIMENSION XND(10000),BNDS(10000),
C DIMENSION TF(10000),TO(10000),T(10000),
C DIMENSION STA(10000),JEN(10000),DISTX(10000),
C DIMENSION BNDS(10000),BB(999),FF(999),
C DIMENSION XX(999),FP(999),
C DIMENSION XXX(999),FFFF(999),
C DIMENSION BNNOR=BNOR+BNOR-BESPL--IWKIN-
C EXTERNAL RNLNLRNSET->RNOR->BNOR->BESPL--IWKIN-
1001 FORMAT(5E12.4)
1002 FORMAT(5E12.4)
1003 FORMAT(14.14)
1004 FORMAT(13.2X,13.2X,2E12.4,2X,13)
1009 FORMAT(13)
1010 FORMAT(13)
1011 FORMAT(1E12.4)
15 1012 C LOGNORMAL ULTIMATE TENSILE STRENGTH--SF.
      READ(3,1002) ISEED,NTOT
      WRITE(3,1002) ISEED,NTOT
      READ(3,1011) XM,XS
      WRITE(3,1011) XM,XS
      YS = SORT(LOG((1.0+(XS/XM)**2.))
      YH = LOG(XM)-0.5*YS**2.
      CALL RNSET(ISEED)
      CALL RNLNLRNSET(YM,YS,SF)
      WRITE(6,2020)
      2 2020 FORMAT('LOGNORMAL SF')
      WRITE(6,1001)(SF(I),I=1,NTOT)
      C LOGNORMAL FATIGUE STRENGTH--XLNMF
      WRITE(6,1002) ISEED,CYCLE=XLNMF
      READ(3,1011) XM,XS
      WRITE(3,1011) XM,XS
      YS = SORT(1.0-(XS/XM)**2.)
      YH = LOG(XM)-0.5*YS**2.
      CALL RNSET(ISEED)
      CALL RNLNLRNSET(YM,YS,XLNMF)
      WRITE(6,2021)
      2021 FORMAT('LOGNORMAL XLNMF')
      3 3 WRITE(6,1001)(XLNMF(I),I=1,NTOT)
      C LOGNORMAL FATIGUE STRENGTH AT REFERENCE CONDITIONS, SO
      WRITE(6,1002) ISEED,MIDI
      READ(3,1011) XM,XS
      WRITE(3,1011) XM,XS
      YS = SORT(LOG(1.0+(XS/XM)**2.))
      YH = LOG(XM)-0.5*YS**2.
      CALL RNSET(ISEED)

```

ORIGINAL PAGE IS
OF POOR QUALITY

```

C      WRITE(6,202)
C      FORMAT(6,1001) I=1,NTOT
C      C LOGNORMAL (LOG OF REFERENCE CYCLES, XLNMO
C      WRITE(6,1002) ISEED,NTOT
C      READ(3,1011) XM, XS
C      WRITE(6,1011) XM, XS
C      XS = SORT(XLOG(1.0+(XS/XM)**2))
C      YM = LOG(XM)-0.5*YS**2
C      CALL RNSET(ISEED)
C      2023 WRITE(6,2023)
C      FORMAT(6,1001) I=1,NTOT
C      WRITE(6,1001) XLNMO(I), I=1,NTOT
C      C LOGNORMAL STRENGTH AT CURRENT CONDITIONS. S
C      WRITE(6,1002) ISEED,NTOT
C      READ(3,1011) XM, XS
C      XS = SORT(XLOG(1.0+(XS/XM)**2.))
C      YM = LOG(XM)-0.5*YS**2.
C      CALL RNSET(ISEED)
C      CALL RNLN(NTOT, YM, YS, S)
C      2024 FORMAT(6,2024)
C      WRITE(6,2024)
C      C DEFINE RANDOM STRESSES
C      C LOGNORMAL REFERENCE STRESS. S160
C      WRITE(6,1002) ISEED,NTOT
C      READ(3,1011) XM, XS
C      WRITE(6,1011) XM, XS
C      XS = SORT(XLOG(1.0+(XS/XM)**2.))
C      YM=LOG(XM)-0.5*YS**2.
C      CALL RNSET(ISEED)
C      CALL RNLN(NTOT, YM, YS, SIG0)
C      C CHANGE SIG0 TO NEGATIVE VALUES FOR COMPRESSIVE
C      C RESIDUAL STRESSES
C      DO 201 I = 1,NTOT
C      SIG0(I)=-SIG0(I)
C      201 CONTINUE
C      2036 FORMAT(6,2036)
C      WRITE(6,2036)
C      C LOGNORMAL CURRENT STRESS, SIG
C      WRITE(6,1001) ISEED,NTOT
C      READ(3,1011) XM, XS
C      XS = SORT(XLOG(1.0+(XS/XM)**2.))
C      YM=LOG(XM)-0.5*YS**2.
C      CALL RNSET(ISEED)
C      CALL RNLN(NTOT, YM, XS, SIG)
C      WRITE(6,2037)
C      2037 FORMAT(6,LOGNORMAL SIG')
C      WRITE(6,1001) SIG(I), I=1,NTOT
C      C NORMAL EXPONENTS - XN, XXN, XQ
C      WRITE(6,1002) ISEED,NTOT
C      READ(3,1011) YM, YS
C      WRITE(6,1011) YM, YS
C      CALL RNSET(ISEED)
C      CALL RNNOR(NTOT, XN)
C      DO 202 I=1,NTOT
C      XN(I)=YSXXN(I)+YM
C      202 CONTINUE
C      WRITE(6,2025)

```

```

2025 FORMAT('NORMAL',XNM(1),I=1,NTOT)
      WRITE(6,1001)(XNM(I),I=1,NTOT)
      WRITE(6,1002)ISEED,NTOT
      CALL RNNOR(NTOT,XNM)
      DO 203 I=1,NTOT
        XNM(I)=YS*XXM(I)+YM
203  CONTINUE
      WRITE(6,2026)
      FORMAT('NORMAL XXM',I=1,NTOT)
      WRITE(6,1003)(XXM(I),I=1,NTOT)
      WRITE(6,1004)ISEED,NTOT
      CALL RNNSE(NTOT)
      CALL RNNOR(NTOT,XXM)
      DO 204 I=1,NTOT
        XXQ(I)=YS*XXQ(I)+YM
204  CONTINUE
      WRITE(6,2027)
      FORMAT('NORMAL XXQ',I=1,NTOT)
      WRITE(6,1001)(XXQ(I),I=1,NTOT)
      C NORMAL TEMPERATURES, TF TO T
      C NORMAL FINAL (MELTING) TEMPERATURE, TF
      WRITE(6,1002)ISEED,NTOT
      READ(3,1011)YM,YS
      WRITE(6,1011)YM,YS
      CALL RNNSE(NTOT)
      CALL RNNOR(NTOT,TF)
      DO 205 I=1,NTOT
        TF(I)=YS*TF(I)+YM
205  CONTINUE
      WRITE(6,2046)
      FORMAT('NORMAL TF',I=1,NTOT)
      WRITE(6,1001)(TF(I),I=1,NTOT)
      C NORMAL REFERENCE TEMPERATURE, T0
      WRITE(6,1002)ISEED,NTOT
      READ(3,1011)YM,YS
      WRITE(6,1011)YM,YS
      CALL RNNSE(NTOT)
      CALL RNNOR(NTOT,T0)
      DO 206 I=1,NTOT
        T0(I)=YS*T0(I)+YM
206  CONTINUE
      WRITE(6,2047)
      FORMAT('NORMAL T0',I=1,NTOT)
      WRITE(6,1001)(T0(I),I=1,NTOT)
      C NORMAL CURRENT TEMPERATURE, T
      WRITE(6,1002)ISEED,NTOT
      READ(3,1011)YM,YS
      WRITE(6,1011)YM,YS
      CALL RNNSE(NTOT)
      CALL RNNOR(NTOT,T)
      DO 207 I=1,NTOT
        T(I)=YS*T(I)+YM
207  CONTINUE
      WRITE(6,2048)
      FORMAT('NORMAL T',I=1,NTOT)
      WRITE(6,1001)(T(I),I=1,NTOT)
      C CALCULATE LOG OF CURRENT CYCLES, LOG XNM
      DO 102 I=1,NTOT
        RS=((SF(I)-SIG(I))/(SF(I)-SIG(I)))*XXM(I)
        TEMP=((TF(I)-T(I))/(TF(I)-T(I)))*XXN(I)
        XNM1=(S(I)/(SO(I)*TEMP*RS))*XX(I)
        XNM2=(XNM(I)-(XNM(I)-XNM(I)))*XXN(I)
        IF (XNM2.LT.0.0) XNM2=0.0

```

```

      XNM=I-XNM2
      102 CONTINUE
      WRITE(6,2028)
      2028 FORMAT(' LOG OF CYCLES TO REACH MEAN FATIGUE STR = ',/)
      1 150(MPA'1001(XNM(I),I=1,NTOT)
      C - C SORT LOG OF CYCLES
      CALL SORT(XNM,NTOT)
      C 2029 FORMAT(' LOG OF CYCLES')
      C 2029 FORMAT(' LOG OF CYCLES',INIT,XNM,I=1,NTOT)
      C CALCULATE PDF OF LOG OF CURRENT CYCLES,LOG XNM
      READ(3,1009)NODE,INIT,ALPHA,EPS,MAXIT
      WRITE(6,985)
      985 FORMAT(' DESPL. PARAMETERS')
      WRITE(6,1009)NODE,INIT,ALPHA,EPS,MAXIT
      BNDSC(1)=XNM(1)-0.05*XNM(1)
      BNDSC(2)=XNM(NTOT)+0.05*XNM(NTOT)
      WRITE(6,979)BNDSC(1),BNDSC(2)
      979 FORMAT(' BNDSC(1),BNDSC(2)='E12.4,IX,E12.4)
      CALL DESPL(NTOT,XNM,NODE,BNDSC,INIT,ALPHA,MAXIT,EPS,DENS,STAT,
      1MISS)
      WRITE(6,980)
      980 FORMAT(' PDF OF LOG OF CURRENT CYCLES.LOG XNM,Y AXIS OF PDF PLOT')
      WRITE(6,1001)(DENS(I),I=1,NNODE)
      WRITE(6,981)
      981 FORMAT(' OUTPUT STATISTICS')
      WRITE(6,1001)(STAT(I),I=1,4)
      WRITE(6,982)
      982 FORMAT(' NUMBER OF MISSING VALUES')
      WRITE(6,1010)NNODES
      C CALCULATE WINDOW WIDTH, HH
      C HH=(BNDSC(2)-BNDSC(1))/(NNODE-1)
      C CALCULATE VALUES OF LOG OF CURRENT CYCLES AT WHICH PDF IS ESTIMATED;
      C ALSO CALLED 'NODE' VALUES
      DO 6001 I=1,NNODE-2
      BNDSC(I+2)=BNDSC(I) + (I*HH)
      6001 CONTINUE
      WRITE(6,983)
      983 FORMAT(' LOG OF CURRENT CYCLES, LOG XNM')
      WRITE(6,1001)(BNDSC(I),I=1,NNODE)
      C REORDER BNDSC FOR PLOTTING
      C
      C SAVE1 = BNDSC(2)
      C SAVE2 = BNDSC(NODE)
      C BNDSC(NODE)=BNDSC(2)
      DO 6002 I=1,NNODE-2
      BNDSC(I+1)=BNDSC(I+2)
      6002 CONTINUE
      BNDSC(NODE-1)=SAVE2
      C
      C WRITE(6,984)
      984 FORMAT(' ORDERED LOG OF CURRENT CYCLES, LOG, XNM',
      1 1X,AXIS PLOT.CDF PLOT)
      C WRITE(6,1001)(BNDSC(I),I=1,NNODE)
      C LOG XNM TO PLOT FILES
      C WRITE(34,990)
      990 FORMAT(' (E12.4,IX,E12.4)',/

```

**ORIGINAL PAGE IS
OF POOR QUALITY**

```

      READ(3,1010)IOPT
      WRITE(6,1920)
      FORMAT(' ', ' BNDSDISTPLOT')
      WRITE(6,1010)IOPT
      DO=6003+I=1,NODE
      P=GCDF(X0,IOPT,NODE,BNDS,DENS)
      BNDSX(I)=X0
      Y0=X0+HH
      DISTX(I)=F
      CONTINUE
      WRITE(6,1940)
      FORMAT(' ', ' CDF OF LOG OF CURRENT CYCLE')
      994 FORMAT(' ', ' PDF OF LOG OF CURRENT CYCLE')
      993 FORMAT(' ', ' ORDERED LOG OF CURRENT CYCLE')
      1 X AXIS OF PDF, CDF PLOT'
      WRITE(6,1001)(BNDS(I),I=1,NODE)
      WRITE(6,1001)(BNDSX(I),I=1,NODE)
      WRITE(6,1001)(DISTX(I),I=1,NODE)
      C WRITE LOG OF CURRENT CYCLES AND CDF OF LOG
      C TO THE PLOT FILES
      WRITE(35,990)
      STOP
      ENDROUTINE SORTLY(N)
      DIMENSION Y(10000)
      N1=N-1
      DO 1 I=1, N1
      J=1+I
      K=J, N
      DO 2 K=J, N
      Y(K)=Y(I)
      TEMP=Y(I)
      Y(I)=Y(K)
      Y(K)=TEMP
      2 CONTINUE
      1 CONTINUE
      RETURN
      END

      C IMSL Name: D3SPL/DD3SPL Single/Double
      Computer: IBM/SINGLE
      Revised: November 1, 1985
      Purpose: Nonparametric probability estimation by the penalized
      Use: CALL DISPL(NODES, NODE, DENS, STAT, HEW, WK2)
      Arguments:
      NODES - Number of observations.

```

Vector of length NOBS containing the random sample
 responses. (Input)
 NODE - Number of mesh nodes for the discrete pdf estimate.
 (Input)
 BNDS - Vector of length 2 containing the minimum and maximum
 values for X(i) in BNDS(1) and BNDS(2), respectively.
 (Input)
 INIT - Initialization option. (Input)
 ALPHA - Positive Penalty weighting factor which controls the
 smoothness of the estimate. (Input)
 MAXIT - Maximum number of iterations allowed in the iterative
 procedure. (Input)
 EPS - Convergence criterion. (Input)
 DENS - Vector of length NODE containing the estimated values of
 the discrete pdf at the NODE equally spaced mesh nodes.
 (Input/Output if INIT=1, Output otherwise)
 STAT - Vector of length 4 containing the statistics. (Output)
 STAT(1) and STAT(2) contain the log-likelihood and the
 log-penalty terms, respectively. STAT(3) and STAT(4)
 contain the estimated mean and variance for the
 estimated density.
 HESS - Seven by NODE-2 hessian matrix (and its factorization).
 LDHESS - Leading dimension of HESS exactly as specified in the
 dimension statement in the calling program. (Input)
 ILOHI - NODE by 2 matrix containing the indices for the risk set
 of each node value. (Output)
 DENEST - NODE by 3 matrix containing the gradient vector, among
 other quantities. (Output)
 B - Vector of length NODE containing the NODE values.
 INPUT - Pivot vector of length NODE-2. (Output)
 WK2 - Work vector of length NODE-2. (Output)

Chapter: SPATIAL LIBRARY Density and Hazard Estimation

Copyright: 1985 by IMSL, Inc. All Rights Reserved.
 Warranty: IMSL warrants only that IMSL testing has been applied
 to this code. No other warranty, expressed or implied,
 is applicable.

```

30 C SUBROUTINE DISPL (NOBS, X, NODE, BNDS, INIT, ALPHA, MAXIT, EPS,
31          DENS, STAT, HESS, ILOHI, DENEST, B,
32          IPUL, WK2) SPECIFICATIONS FOR ARGUMENTS,
33          NOBS, NODE, INIT, MAXIT, LDHESS, ILOHI(NODE,*),
34          IPUL(*), BNDS(2), DENS(4), STAT(4),
35          ALPHA, EPS, X(4), HESS(NODE,*), DENSE(NODE,*), WK2(*),
36          IPUL, WK2) SPECIFICATIONS FOR LOCAL VARIABLES,
37          INTEGER I2, IMPR, IPTR, ITER, K, KM1, KM2, KP1, KP2, M, HOLD,
38          REAL BK, BMAX1, BMAX2, CK, CKH1, CKH2, CKMCH1, CKP1, CKP2,
39          CONS, EPS1, FACTOR, FK, FKM1, FKM2, FKPI, H, H2, H3,
40          DOUBLE PRECISION SUM1, SUM2, SUM3, TEMP, WK(4),
41          INTEGER MINCR(8),
42          SAVE MINCR
43          SPECIFICATIONS FOR SAVE VARIABLES
44          intrinsic abs,max,min,mod,sort
  
```

```

      INTRINSIC MAX0, MIN0, MOD, -99RT
      INTEGER MAX0, MIN0, MOD
      REAL ALDG, AMAX1, SQR7
      SPECIFICATIONS FOR SURROUNTING
      EXTERNAL EIMES, EIFSH, EISIR, EISITR, SADD, SAXFY,
      EXTERNAL SHPROD, DSSCAL, DSSPT, LAFTR, LFSRR
      SPECIFICATIONS FOR FUNCTIONS
      EXTERNAL ISMIN, NIRCD, SDOT, SNRM2, SSUM
      INTEGER ISMIN, NIRCD, SDOT, SNRM2, SSUM
      DATA MINCR/5, 9, 17, 33, 65, 129, 253, 100001/
      CALL EIPSH ('D3SPL')          Error-checks
      NER = 1
      IF (NOBS .LE. 1) THEN
        CALL EIMES (5, 1)           After removing all missing (NaN, not-a-number)
        CALL EIMES (5, 1)           values from x there are no valid observations.
        CALL EIMES (5, 1)           At least one valid observation is necessary.
      END IF
      IF (NODE .LE. 4) THEN
        CALL EISTR (1, NODE)
        CALL EIMES (5, 1, NODE = % (11). The number of mesh nodes, NODE, must be an odd integer greater than 3.
      ELSE IF (MOD (NODE, 2) .EQ. 0) THEN
        CALL EISTR (1, NODE)
        CALL EIMES (5, 3, NODE = % (11) must be an odd integer greater than 4.
      END IF
      IF (ALPHA .LE. 0.0) THEN
        CALL EISTR (1, ALPHA)
        CALL EIMES (5, 1, ALPHA = % (R1). The penalty-weighting factor which controls smoothness, ALPHA, must be greater than 0.)
      END IF
      IF (MAXIT .LE. 0.0) THEN
        CALL EISTR (1, MAXIT)
        CALL EIMES (5, 5, MAXIT = % (11). The maximum number of iterations, MAXIT, must be greater than 0.)
      END IF
      IF (BND$ (1) .GT. BND$ (2)) THEN
        CALL EISTR (1, BND$ (1))
        CALL EISTR (2, BND$ (2))
        CALL EIMES (5, 6, BND$ (1) = % (R1) and BND$ (2) = % (R2). The minimum value for X, BND$ (1), must be less than or equal to the maximum value for X, BND$ (2).)
      END IF
      IF (INIT .NE. 0) THEN
        IF (DENS (1) .NE. 0 .OR. DENS (NODE) .NE. 0) THEN
          CALL EISTR (1, DENS (1))
          CALL EISTR (2, DENS (NODE))
          CALL EISTR (1, NODE)
          CALL EIMES (5, 7, DENS (1) = % (R1) and DENS (NODE) = % (11) // estimates of the density must be zero.)
        END IF
        IF (DENS (ISMIN (NODE, DENS, 1)) .LT. 0) THEN
          CALL EIMES (5, 8, The initial estimates of the density, DENS, must be greater than or equal to 0.)
      END IF

```

```

      END IF
      NOB1 = 0
      DO 10 I=1, NOBS, 1
        IF (X(I) .LT. BNDS(1) .OR. X(I) .GT. BNDS(2)) THEN
          NOB1 = NOB1 + 1
        END IF
      10 CONTINUE
      IF (NOB1 .EQ. NOBS) THEN
        CALL EINES ('$', //, //)
        ! All elements in X lie outside the interval BNDS(1) to BNDS(2). At least one element of X must lie in this interval.
      ELSE
        EPS1 = EPS
        END IF
        IF (EPS1 .LE. 0.0) THEN
          EPS1 = 1.0E-4
        ELSE
          EPS1 = EPS
        END IF
        IF (NIRCD(0) .NE. 0) GO TO 2000
        Initialization
      C
      IMPTR = 0
      C IF (INIT .EQ. 0) THEN
        Set initial densities
        DENS(1) = 0.0
        DENS(2) = 2.0 / (BNDS(2) - BNDS(1))
        DENS(3) = 0.0
        M = 3
      ELSE
        NODE = NODE
      END IF
      C 20 IF (INIT .EQ. 0) THEN
        Refine mesh
        MOLD = M
        IMPTR = IMPTR + 1
        M = MIN(NGDE, MINC+IMPTR)
      END IF
      C
      H = (BNDS(2)-BNDS(1))/(M-1)
      Get mesh interval width
      H2 = H*XH
      H3 = H2*XH
      Make initial DENS integrate to 1.
      C IF (INIT .NE. 0) THEN
        END IF
        CALL SSCL (NODE, 1.0/(H*SSUM(NODE,DENS-1)), DENS, 1)
        Set mesh nodes
      C
      B(1) = BNDS(1)
      DO 30 I=2,M
        B(I) = B(I-1) + H
      30 CONTINUE
      C
      IMPTR = 0
      Set B indices for interpolating X
      40 IMPTR = IMPTR + 1
      IF (X(IMPTR) .LT. BNDS(1)) GO TO 40
      DO 60 K=1, N - 1
        ILOH(K,1) = IMPTR
        ILOH(K,2) = IMPTR
        IF (IMPTR .LE. NOBS) THEN
          IF (X(IMPTR) .LT. BNDS(2)) THEN
            IF (ILOH(K,2) .LT. ILOH(K,1)) THEN
              IMPTR = IMPTR + 1
            ELSE
              IMPTR = IMPTR + 1
            END IF
          END IF
        60 CONTINUE
        GO TO 50
      41 IF (IMPTR .LE. NOBS) GO TO 50
      42 END IF
      60 CONTINUE

```

```

C-----79-FACTOR-----27-OCT-PHYS----- Initialize mesh node sensitivities
C
C      IF (INIT .EQ. 0) THEN          Via DESPT
C        CALL DESPT (M**2, B(2), 1, MOLD, BNDS, DENS, DENSET, JK, UK,
C
C        UK = 1.0/(H*XKH)
C        TEMP = 1.0/(H*XKH)
C        DO 30 I=2, M-1
C          DENS(I) = AMAX1(TEMP, SQRT(DENSET(I-1,1)))
C
C        30  CONTINUE
C
C      ELSE                           Via the initial estimates
C
C        DO 70 I=2, M-1
C          DENS(I) = SQRT(DENS(I))
C
C        70  CONTINUE
C
C      ENDIF
C      DENS(H) = 0.0
C
C      C-----DO-140-----ITER=1--MAXIT----- Maximize
C
C      HESS(1,1) = 0.0
C      HESS(1,2) = 0.0
C      HESS(2,1) = 0.0
C      BSMALL = 0.0
C      SUM = 0.0
C
C      C-----DO-120-----K=2--M-1----- Get Hessian - Lagrangian
C
C      KM1 = K-1
C      KM2 = MAX0(1,K-2)
C      KP1 = K+1
C      KP2 = MIN0(K,K+2)
C
C      FK = DENS(K)
C      FKM1 = DENS(KM1)
C      FKM2 = DENS(KM2)
C      CK = FKM1**2
C      CK = FKM2**2
C      CKP1 = DENS(KP1)**2
C      CKP2 = DENS(KP2)**2
C      BK = B(K)
C      BK1 = B(KM1)
C      SUM = SUM + CK
C      IF (K .GE. 4) HESS(4,4) = 4.0*FK*FKM2*FACTOR
C
C      SUM1 = 0.0D0
C      SUM2 = 0.0D0
C      SUM3 = 0.0D0
C      DO 100 I=LOHI(K,1), LOHI(K,2)
C        SUM1 = SUM1 - CONS*(CKP1-CK)*TEMP
C        TEMP = (X(I)-BK)/H
C        CONS = (1.0-TEMP)/(CK+(CKP1-CK)*TEMP)
C        SUM2 = SUM2 + CONS*CONS
C
C      100  CONTINUE
C      CKM1 = CK - CKM1
C      DO 110 I=LOHI(KM1,1), LOHI(KM1,2)
C        CONS = (X(I)-BKMH)/H
C        TEMP = CKMH + CKMH*CONS
C        SUM1 = SUM1 - CONS*CONS/TEMP
C        TEMP = TEMP*TEMP
C        SUM2 = SUM2 + CONS*CONS/TEMP
C
C      110  CONTINUE
C      TEMP = FACTOR*(CKMH2+CKP2-4.0*(CKM1+CKP1)+6.0*CK) + SUM1
C
C      TEMP = 2.0*TEMP
C      BSMALL = BSMALL + 2.0*CK*TEMP

```

```

HES<-3*NH-1--TEMP--4*FACTR*5.*FACTOR+SUM2
IF (K .NE. 2) HESS(2,KM1) = 4.0*FK*FKM1*(-4.0)*FACTR+SUM3
DENEST(KM1,1) = FK*TEMP
DENEST(KM1,2) = -2.0*TEMP
CONTINUE
BSMALL = 1.0/H - SUM + BSMALL
          Save portion of DENEST
C      CALL SCOPY (M-2, DENEST(1,2), 1, DENEST(1,3), 1)
C      CALL SADD (M-2, -BSMALL/(2.0*SUM), HESS(3,1), LDHESS)
C      CALL SCOPY (M-4, HESS(1,3), LDHESS, HESS(5,1), LDHESS)
HESS(5,M-3) = 0.0
HESS(5,M-2) = 0.0
HESS(3,M-2) = 0.0
HESS(4,M-2) = 0.0
          Finish with the hessian
          Fill-out symmetric band structure
C      CALL L2TRB (M-2, HESS, LDHESS, LDHESS, LDHESS, LDHESS)
C      CALL LFSRB (M-2, HESS, LDHESS, LDHESS, LDHESS, LDHESS)
C      CALL LFSRB (M-2, HESS, LDHESS, LDHESS, LDHESS, LDHESS)
          Solve symmetric band linear system
C      IF (N1RCD(1) .NE. 0) GO TO 2000
          Compute the constant
C      CONS = SDOT(M-2,DENEST(1,3),1,DENEST(1,2),1)
C      CONS = (1.0/H-SUM-SDOT(M-2,DENEST(1,3),1,DENEST(1,1),1))/CONS
          Update the gradient
C      CALL SAXPY (M-2, CONS, DENEST(1,2), 1-DENEST(1,1), 1)
          Parameter updates
C      CALL SAXPY (M-2, -1.0, DENEST(1,1), 1, DENS(2), 1)
          Check the convergence criterion
C      TEMP = SNRM2(M-2*DENS(2),1)
          IF (SNRM2(M-2,DENEST,1) .LT. EPSIXTEM) GO TO 150
          Ad hoc projection to plus quadrant
NC      TEMP = TEMP*X1*OE-4/SQRT(M-2.0)
DO 130 I=2,M-1
      DENS(I) = AMAX1(TEMP,DENS(I))
CONTINUE
130 CONTINUE
140 CONTINUE
          Maximum number of iterations //
          CALL EISME (3, 1) The maximum number of iterations //
          IF (MAXIT>=(I1)) was exceeded
          CALL SHPROD (M-2,DENS(2), 1-DENS(2), 1-DENS(2), 1)
          Replace DENS(*) with squares
C      IF (H .NE. NODE) GO TO 20
          Evaluate log likelihood and penalty
C      SUM1 = 0.0
          Penalty
C      DO 160 K=1,M
          KH1 = MAX0((K-1)*1)
          KP1 = MIN0((K+1)*1)
          SUM1 = MIN0(KT1,M)
          SUM1 = (DENS(KM1)-2.0*DENS(KP1)+DENS(KP1))/X1*X2
160 CONTINUE
          SUM1 = SUM2 + ALOG(DENEST(1,1))
          Log-likelihood
C      DO 170 I=1, NOBS
          IF ((X(I).GE.BNDS(1)) AND (X(I).LE.BNDS(2))) THEN
              CALL D2SPX (1,X(I), 1, NODE, BNDS, DENS, DENEST, WK, WK,
              STAT(2) = -0.5*FACTOR*XSUM1
              SUM2 = 0.0
170 CONTINUE
          END IF
          SUM2 = SUM2 + ALOG(DENEST(1,1))
          Evaluate H.L.P.E. mean and variance

```

```

SUM1 = 0.0
SUM2 = 0.0
DO 130 K=1, M - 1
  FN = DENS(K)
  FK1 = DENS(K+1)
  BK = B(K)
  CONS = FK1 + FK1
  TEMP = CONS + FK1
  SUM1 = SUM1 + H2*TEMP/6.0 + 0.5*H*BK*CONS
  SUM2 = SUM2 + H3*(TEMP+FK1)/12.0 + H2*BK*TEMP/3.0 +
  130 CONTINUE
  STAT(3) = SUM1
  STAT(4) = SUM2 - SUM1*SUM1      Exit section
  RETURN E1POP ('DJSPL')
C 9000 CALL E1POP ('DJSPL')
END
/EOF/

```

ORIGINAL PAGE IS
OF POOR QUALITY

ପ୍ରକାଶମ

THE JOURNAL OF CLIMATE

File -DUAO:[CINORMAL.INP]41 (252,111,0), last revised on 22-DEC-1988 13:01, is a 1 block sequential file owned by VIC [DECNET]. The records are variable length with implied (CB) carriage control. The record length is 70 bytes.

Job NORMAL (129) queued to TERM51A120A on 22-DEC-1988 13:01 by user DECPNT, UIC (DECNET), under account DECPNT at priority 100,

900.0000 45.0000
3.0000 3.0000
500.0000 25.0000
100.0000 12.5000
250.0000 11.5000
150.0000 7.5000
150.0000 0.3150
1500.0000 75.0000
200.0000 25.0000
350.0000 20.00
21.0 1.0E-05 30

ORIGINAL PAGE IS
OF POOR QUALITY

**ORIGINAL PAGE IS
OF POOR QUALITY**

File DBAO: [IRANDC3.CPR, 1 (383, 943, 0)] last revised on 23-NOV-1988 11:26, is a 33 block sequential file owned by UIC [11, 111]. The records are variable length with FORTRAN (FTN) carriage control. The longest record is 120 bytes.

Job RANDC3-(689)-queued-to-SYSESBSPRT-on-23-NOV-1988-11:27-by-uap-NETRGNPR14-UIG-E11-111J-under-account-2010ADD-34-priority-100-started-on-printer_TTF7-on-23-NOV-1988 11:27 from queue TTF7.

**ORIGINAL PAGE IS
OF POOR QUALITY**

**ORIGINAL PAGE IS
OF POOR QUALITY**

| DCDF PARAMETERS | | DF LOG OF CURRENT CYCLES | LOG KHN | DF LOG OF CURRENT CYCLES | LOG KHN | DF LOG OF CURRENT CYCLES | LOG KHN |
|-----------------|-------------|--------------------------|-------------|--------------------------|-------------|--------------------------|-------------|
| 0. 5743E+01 | 0. 5919E+01 | 0. 6115E+01 | 0. 6115E+01 | 0. 6115E+01 | 0. 6115E+01 | 0. 6115E+01 | 0. 6115E+01 |
| 0. 6742E+01 | 0. 6898E+01 | 0. 7094E+01 | 0. 6696E+01 | 0. 6742E+01 | 0. 6742E+01 | 0. 6742E+01 | 0. 6742E+01 |
| 0. 7682E+01 | 0. 8000E+01 | 0. 8072E+01 | 0. 6858E+01 | 0. 7682E+01 | 0. 7682E+01 | 0. 7682E+01 | 0. 7682E+01 |
| 0. 8655E+01 | 0. 8855E+01 | 0. 8951E+01 | 0. 7844E+01 | 0. 8655E+01 | 0. 8655E+01 | 0. 8655E+01 | 0. 8655E+01 |
| 0. 9638E+01 | | | | 0. 9638E+01 | 0. 9638E+01 | 0. 9638E+01 | 0. 9638E+01 |
| 0. 5743E+01 | 0. 5919E+01 | 0. 6115E+01 | 0. 6115E+01 | 0. 6115E+01 | 0. 6115E+01 | 0. 6115E+01 | 0. 6115E+01 |
| 0. 6742E+01 | 0. 6898E+01 | 0. 7094E+01 | 0. 6696E+01 | 0. 6742E+01 | 0. 6742E+01 | 0. 6742E+01 | 0. 6742E+01 |
| 0. 7682E+01 | 0. 8000E+01 | 0. 8072E+01 | 0. 6858E+01 | 0. 7682E+01 | 0. 7682E+01 | 0. 7682E+01 | 0. 7682E+01 |
| 0. 8655E+01 | 0. 8855E+01 | 0. 8951E+01 | 0. 7844E+01 | 0. 8655E+01 | 0. 8655E+01 | 0. 8655E+01 | 0. 8655E+01 |
| 0. 9638E+01 | | | | 0. 9638E+01 | 0. 9638E+01 | 0. 9638E+01 | 0. 9638E+01 |

ORIGINAL PAGE IS
OF POOR QUALITY

ପ୍ରକାଶକ
ନିବାସ
ମୁଦ୍ରଣ
ପାତ୍ର
ବାଲକ
ବାଲକ
ବାଲକ
ବାଲକ

The image displays a large grid of binary code patterns, likely representing memory dump data. The patterns are organized into several columns and rows. The first column contains vertical sequences of '0's and '1's. The second column features horizontal '0' and '1' bands. The third column shows diagonal '0' and '1' bands. The fourth column consists of repeating 'P' and 'R' symbols. The fifth column contains 'E' and 'Z' symbols. The sixth column has 'F' and 'C' symbols. The seventh column displays 'D' and 'B' symbols. The eighth column features 'G' and 'H' symbols. The ninth column contains 'A' and 'S' symbols. The tenth column shows 'T' and 'U' symbols. The eleventh column has 'V' and 'W' symbols. The twelfth column displays 'X' and 'Y' symbols. The thirteenth column features 'N' and 'M' symbols. The fourteenth column contains 'L' and 'K' symbols. The fifteenth column shows 'J' and 'I' symbols. The sixteenth column displays 'H' and 'G' symbols. The十七th column features 'F' and 'E' symbols. The eighteen column contains 'D' and 'C' symbols. The nineteen column shows 'B' and 'A' symbols. The twenty column displays 'S' and 'R' symbols. The twenty-one column features 'W' and 'P' symbols. The twenty-two column contains 'U' and 'Q' symbols. The twenty-three column shows 'V' and 'O' symbols. The twenty-four column displays 'Y' and 'N' symbols. The twenty-five column features 'X' and 'M' symbols. The twenty-six column contains 'Z' and 'L' symbols. The twenty-seven column shows 'T' and 'K' symbols. The twenty-eighth column displays 'F' and 'J' symbols. The twenty-ninth column features 'C' and 'H' symbols. The thirty column contains 'G' and 'I' symbols. The thirty-one column shows 'B' and 'D' symbols. The thirty-second column displays 'E' and 'A' symbols. The thirty-third column features 'P' and 'S' symbols. The thirty-four column contains 'R' and 'W' symbols. The thirty-fifth column shows 'Q' and 'U' symbols. The thirty-six column displays 'V' and 'N' symbols. The thirty-seventh column features 'O' and 'Z' symbols. The thirty-eighth column contains 'M' and 'T' symbols. The thirty-nine column shows 'L' and 'F' symbols. The forty column displays 'K' and 'G' symbols. The forty-one column features 'J' and 'B' symbols. The forty-two column contains 'I' and 'D' symbols. The forty-three column shows 'H' and 'C' symbols. The forty-four column displays 'G' and 'E' symbols. The forty-five column features 'F' and 'A' symbols. The forty-six column contains 'E' and 'S' symbols. The forty-seven column shows 'D' and 'R' symbols. The forty-eight column displays 'C' and 'P' symbols. The forty-nine column features 'B' and 'Q' symbols. The五十th column contains 'A' and 'M' symbols. The fifty-one column shows 'S' and 'L' symbols. The fifty-two column displays 'R' and 'K' symbols. The fifty-three column features 'P' and 'J' symbols. The fifty-four column contains 'Q' and 'H' symbols. The fifty-five column shows 'U' and 'G' symbols. The fifty-six column displays 'V' and 'F' symbols. The fifty-seven column features 'W' and 'D' symbols. The fifty-eight column contains 'X' and 'C' symbols. The fifty-nine column shows 'Y' and 'B' symbols. The六十th column displays 'Z' and 'A' symbols.

**ORIGINAL PAGE IS
OF POOR QUALITY**

ORIGINAL PAGE IS
OF POOR QUALITY

卷之三

卷之三

卷之三

The image shows a 16x16 grid of symbols, likely representing a convolutional neural network's feature map or a specific layer's output. The symbols are organized into four main vertical columns. The first column contains symbols for padding (P), input data (I), and zero-padding (Z). The second column contains symbols for the first two rows of the kernel (K1, K2). The third column contains symbols for the output feature map (O) and the third row of the kernel (K3). The fourth column contains symbols for the final output row (O) and the fourth row of the kernel (K4). The symbols are arranged in a staggered pattern, indicating a stride of 2 for the convolution operation.

FILE DBAO: CIPR01, last revised on 23-NOV-1988 11:26, is a 2 block sequential file owned by UIC C11,111. The records are variable length with FORTRAN (FTN) carriage control. The longest record is 25 bytes.
JOB PL0T2 (688) queued to SYSSSPRT on 23-NOV-1988 11:26 by user NETMONPRIV, UIC C11,111, under account 2010ADD at priority 100.
started on printer _TTF6: on 23-NOV-1988 11:26 from queue _TTF6.

(E12. 4, IX, E12. 4)
0. 0000E+00
0. 3477E-02
0. 1413E-01
0. 4147E-01
0. 8113E-01
0. 6306E+01
0. 1351E+00
0. 2020E+00
0. 2773E+00
0. 3638E+00
0. 4525E+00
0. 5419E+00
0. 6291E+00
0. 7110E+00
0. 7852E+00
0. 8474E+00
0. 9023E+00
0. 9430E+00
0. 9716E+00
0. 9873E+00
0. 9977E+00
0. 10000E+01

8.0 APPENDIX C

RANDOM4 SAMPLE PROBLEM: SOURCE, INPUT AND OUTPUTFILES

ORIGINAL PAGE IS
OF POOR QUALITY

卷之三

ORIGINAL PAGE IS
OF POOR QUALITY

ORIGINAL PAGE IS
OF POOR QUALITY

```
10 C LOGNORMAL STRENGTH-REFERENCE-CONDITIONS, 50
11 WRITE(5,1005) ISEED,NTOT
12 READ(5,1006) XM,XS
13 XS = 500.
14 C XS = SQRT((LOG(1.0+(XS/XM)**2)-1.0)/0.5*YS**2)
15 YM = LOG((XM)-0.5*YS**2)
16 CALL RNSET(ISEED)
17 CALL RNLN(NTOT,YM,YS,50)
18 WRITE(20,1001)-(50+I)-I-1-NTOT
19 WRITE(6,2023)
20 2022 FORMAT(6,1001), (50(1),I=1,NTOT)
21 C LOGNORMAL LOG-OF REFERENCE CYCLES, XLMNO
22 WRITE(6,1005) ISEED,NTOT
23 READ(5,1006) XM,XS
24 WRITE(2,1006) XM,XS
25 XM = 250.
26 XS = SQRT((LOG(1.0+(XS/YM)**2)-1.0)/0.5*YS**2)
27 YM = LOG((XM)-0.5*YS**2)
28 CALL RNSET(ISEED)
29 CALL RNLN(NTOT,YM,YS,XLMNO)
30 CALL LNHO(1),LNHO(1,NTOT)
31 WRITE(6,2023)
32 2023 FORMAT(6,1001)(XLMNO(1),I=1,NTOT)
33 C LOGNORMAL FATIGUE STRENGTH AT CURRENT CONDITIONS, 5
34 READ(5,1006) XM,XS
35 WRITE(6,1005) XM,XS
36 XS = 125.
37 YM = LOG((XM)-0.5*YS**2)
38 CALL RNSET(ISEED)
39 CALL RNLN(NTOT,YM,YS,S)
40 WRITE(6,2024)
41 2024 FORMAT(6,1001)(S(1),I=1,NTOT)
42 C DEFINE RANDOM STRESSES
43 C LOGNORMAL REFERENCE STRESS, SIG0
44 WRITE(6,1005) ISEED,NTOT
45 READ(5,1006) XM,XS
46 WRITE(6,1004) XM,XS
47 XM = 20.
48 XS = 1.
49 YM = LOG(XM)-0.5*YS**2
50 XS = SORT(1.0*(XS/XM)**2.)
51 YM = LOG(XM)
52 CALL RNSET(ISEED)
53 CALL RNLN(NTOT,YM,YS,SIG0)
54 CHANGE SIG0 TO NEGATIVE VALUES FOR COMPRESSIVE
55 C RESIDUAL STRESSES
56 DO 401 I = 1,NTOT
57 SIG0(I)=-SIG0(I)
58 401 CONTINUE
59 WRITE(6,1001)-(SIG0+I)-I-1-NTOT
60 2036 FORMAT(6,2016)
61 WRITE(6,1001)(SIG0(I),I=1,NTOT)
62 C LOGNORMAL CURRENT STRESS, SIG0
63 WRITE(6,1005) ISEED,NTOT
```

ORIGINAL PAGE IS
OF POOR QUALITY

```
REARLS+1.006*XM**45
      WRITE(6,1006) XM, YS
C
C
      XM= 150.
      XS= 7.5
      YS=SQRT(XM)*(1.0+(XS/XM)**2.)
      YM=LOG(XM)/SQRT(XM)
      CALL RNSET(ISEED)
      CALL RNNR(NTOT,YM,YS,SIG)
      WRITE(27,1001)(SIG(I),I=1,NTOT)
      2037 FORMAT(6,2037)(LOG(NORMAL SIG/I))
      WRITE(6,1001)(SIG(I),I=1,NTOT)
      C NORMAL EXPONENTS, XXN, XM, XXQ
      YM = 0.515
      YS = 0.515 ISEED, NTOT
      WRITE(6,1005) ISEED, NTOT
      READ(5,1006) YM, YS
      WRITE(6,1006) YM, YS
      CALL RNSET(ISEED)
      CALL RNNR(NTOT,XXN)
      DO 101 I=1,NTOT
      XXN(I)=YS*XXN(I)+YM
      XXN(I)=YS*XXN(I)+YM
      101 CONTINUE
      WRITE(23,1001)(XXN(I),I=1,NTOT)
      2025 FORMAT(6,2025,
     1          '(NORMAL XXN',
     1          '(6+100L)XXN)',I=1,NTOT)
      WRITE(6,1005) ISEED, NTOT
      CALL RNSET(ISEED)
      CALL RNNR(NTOT,XXN)
      DO 301 I=1,NTOT
      XXN(I)=YS*XXN(I)+YM
      XXN(I)=YS*XXN(I)+YM
      301 CONTINUE
      WRITE(24,1001)(XXN(I),I=1,NTOT)
      WRITE(6,2026)
      2026 FORMAT(6,2026,
     1          '(NORMAL XXN',
     1          '(XN(I),I=1,NTOT)
      WRITE(6,1005) ISEED, NTOT
      CALL RNSET(ISEED)
      CALL RNNR(NTOT,XXN)
      DO 301 I=1,NTOT
      XXN(I)=YS*XXN(I)+YM
      301 CONTINUE
      WRITE(25,1001)(XXN(I),I=1,NTOT)
      WRITE(6,2027)
      2027 FORMAT(6,2027,
     1          '(NORMAL XXN',
     1          '(XN(I),I=1,NTOT)
      WRITE(6,1005) ISEED, NTOT
      C DEFINE DETERMINISTIC TEMPERATURES
      C TF=500.
      C TO=20.
      C YM=1500.
      C YS=7500.
      C NORMAL TEMPERATURES, TF/TO, T
      C NORMAL FINAL (MELTING) TEMPERATURE, TF
      C WRITE(6,1005) ISEED, NTOT
      C READ(5,1006) YM, YS
      C WRITE(6,1006) YM, YS
      C YS=1500.
      C CALL RNSET(ISEED)
      C CALL RNNR(NTOT,TF)
      DO 405 I=1,NTOT
      TF(I)=YS*TF(I)+YM
      405 CONTINUE
      WRITE(6,2046)
```

```

1946 FORMAT('NORMAL')
      WRITE(6,1001) T(I), I=1,NTOT
      C NORMAL REFERENCE TEMPERATURE
      WRITE(6,1005) ISSEED,NTOT
      READ(6,1006) YM,YS
      WRITE(6,1006) YM,YS
      YN=20.
      YS=0.6
      CALL RNSET(ISEED)
      CALL RNNOR(NTOT,TO)
      DO 406 I=1,NTOT
        TO(I)=YS*T(I)+YM
      CONTINUE
      406 WRITE(6,2047)
      FORMAT('NORMAL TO')
      WRITE(6,1001)(TO(I),I=1,NTOT)
      C NORMAL CURRENT TEMPERATURE
      READ(6,1005) ISSEED,NTOT
      WRITE(6,1006) YM,YS
      YM=350.
      YS=42.
      CALL RNSET(ISEED)
      CALL RNNOR(NTOT,T)
      DO 407 I=1,NTOT
        T(I)=YS*T(I)+YM
      CONTINUE
      407 WRITE(6,2048)
      FORMAT('NORMAL T')
      WRITE(6,1001)(T(I),I=1,NTOT)
      C CALCULATE CURRENT LOG_OF_CYCLES, LOG_XNM
      DO 102 I=1,NTOT
        RS=((SF(I)-SIG(I))/(SF(I)-SIG(I)))*XXXM(I)
        WRITE(6,6876) RS
      102 FORMAT(1X,E12.4)
      TEMP=((TF(I)-T(I))/TF(I))*XXN(I)
      TEMP=(TF(I)-T(I))/TF(I)
      WRITE(6,7876) TEMP
      TEMP=,E12.4
      C7976 FORMAT(1X,E12.4)
      SS=S(I)
      SSO=SO(I)
      XXQ=XXQ(I)
      WRITE(6,1001) SS
      C WRITE(6,1001) SS
      XNM1=(S(I)/(SO(I)*TEMP*RS))*((1./XXQ(I)))
      C8876 FORMAT(1X,E12.4)
      XNM2=(XLNMF(I)-(XLNMF(I)-XLNM0(I))*XNM1)
      C8875 FORMAT(1X,E12.4)
      IF(XNM2.LT.0.0)XNM2=0.0
      C XNM(I)=10.*XXNM2
      102 CONTINUE
      WRITE(28,1001)(XNM(I),I=1,NTOT)
      WRITE(6,2028)
      2028 FORMAT('LOG OF CYCLES TO REACH MEAN FATIGUE STR = ',/)
      1/259 MPA
      WRITE(6,1001)(XNM(I),I=1,NTOT)
      C SORT LOG_OF_CYCLES
      CALL SORT(XNM,NTOT)
      WRITE(6,1001)(XNM,I=1,NTOT)
      WRITE(6,2029)

```

ORIGINAL PAGE IS
OF POOR QUALITY

ORIGINAL PAGE IS
OF POOR QUALITY.

```

      WRITE(34,990)
      WRITE(34,991)
      WRITE(34,991)(BNDS(j),j=1,NODE)
      WRITE(34,991)FORMAT(E12.4,1X,E12.4)

C CALCULATE CDF OF LOG OF CURRENT CYCLES
      IOPT=2

C READ(3,1004)IOPT
      WRITE(6,1001)
      FORMAT('SCDF PARAMETERS')
      992 WRITE(6,1004)IOPT
      X0=BNDS(1,1)
      DO 5003,I=1,NODE
      P=BCDF(X0,IOPT,NODE,BNDS,NDENS)
      BNDSX(I)=X0
      X0=X0+HH
      DISTX(I)=P
      5003 CONTINUE
      WRITE(6,994)
      994 FORMAT('CDF OF LOG OF CURRENT CYCLES, LOG XNM,
     1Y AXIS OF PDF, CDF PLOT')
      WRITE(6,1001)(DISTX(I),I=1,NODE)

C WRITE(6,993)
      993 FORMAT('ORDERED LOG OF CURRENT CYCLES, LOG XNM,
     1X AXIS OF PDF, CDF PLOT')
      WRITE(6,1001)(BNDS(I),I=1,NODE)
      WRITE(6,1001)(BNDSX(I),I=1,NODE)

C WRITE LOG OF CURRENT CYCLES AND CDF OF CURRENT
44 TO THE PLOT FILES
      WRITE(35,990)
      WRITE(35,991)(BNDS(j),DISTX(j),j=1,NODE)
      STOP
      END

C SUBROUTINE SORT(Y,N)
      DIMENSION Y(1000)
      C Y IS THE ARRAY TO BE SORTED
      C AT COMPLETION Y(1) IS SMALLEST VALUE
      C AT COMPLETION Y(N) IS LARGEST VALUE
      N1=N-1
      DO 1 I=1,N1
      1 = I+1
      DO 2 K=J,N
      IF (Y(I)<Y(K)) GO TO 2
      TEMP=Y(I)
      Y(I)=Y(K)
      Y(K)=TEMP
      2 CONTINUE
      1 CONTINUE
      RETURN
      END

C SUBROUTINE SMOM(X,M,NSAMP,SM)
      C CALCULATES SAMPLE CENTRAL MOMENTS
      C X(1) = SAMPLE VALUES, DIMENSION NSAMP
      C M = NUMBER OF MOMENTS DESIRED
      C NSAMP = SAMPLE SIZE
      C SM = VALUE OF MOMENTS, DIMENSION M
      DIMENSION X(10000),SM(10)

```

```

17 C CALCULATE MEAN
18 SUM=0.0
19 DO 1 I=1,NSAMP
20   1 SUM=SUM+X(I)
21   SM=(2.0*SUM)/(NSAMP)
22   IF (SM<1.0) RETURN
23   SUM=0.0
24   DO 2 I=1,NSAMP
25     2 SUM=SUM+(X(I)-SM)*(X(I)-SM)
26     SM=SUM/(FLOAT(NSAMP-1))
27   IF (SM>1.0) RETURN
28   SUM=0.0
29   DO 3 I=1,NSAMP
30     3 SUM=SUM+(X(I)-SM)*(X(I)-SM)
31     SM=(2.0*SUM)/(NSAMP)
32   IF (SM>1.0) RETURN
33   CONTINUE
34 END

SUBROUTINE MEF1(N,CM,XMIN,XMAX,NXF,XF,KSTART,KDATA,AL,CUM)
-- IMPLICIT REAL*8 (A-H,O-Z)
C... EXECUTIVE PROGRAM FOR USING MAXIMUM ENTROPY METHOD CONSTRAINED BY
C... MOMENTS TO GENERATE A DENSITY FUNCTION
C... COMMON/HELP/S(101)XX(16,101),C(8),M
C... DIMENSION AL(*),CM(*),ETA(4),XF(*),CUM(*),C(3),AL2(10)
C... COMMON/NFAIL/
C... ABOVE LINE DIFFERENT FROM TEXT
C... COMMON/MEP1/KPRINT,TOL,MAXFN
C... DATA KPRINT,MAXFN/1,1.E-6,70/
45 IF (N.EQ.1) KSTART=2
C WRITE THE INPUT DATA
C IF (KDATA.EQ.0) GO TO 1
1 WRITE (6,2)
2 WRITE (6,25) KDATA
3 WRITE (6,26) KPRINT
4 WRITE (6,28) N
5 WRITE (6,29) XMAX
6 WRITE (6,30) XMIN
7 WRITE (6,31) (CM(I),I=1,4)
8 IF (N.GT.4) WRITE (6,21) (CM(I),I=5,N)
9 IF (ABS(CM(1)).LT.1.E-4) GO TO 48
10 WRITE (6,32) TOL
11 WRITE (6,33) NXP
12 CONTINUE
13 1
14 IF (NFAIL.EQ.0)
15 H=3
16 X2MIN=0.0
17 X2MAX=1.
18 C SAVE CM
19 DO 100 I=1,N
20   100 CC(I)=CM(I)
21 C CALCULATE THE MOMENTS AT THE MODIFIED LIMITS
22 C CALL TRN1 (XMAX,XMIN,CC,X2MAX,X2MIN,N)
23 C CALCULATE THE MOMENTS ABOUT THE ORIGIN FOR THE MODIFIED LIMITS.
24 C STORE THEM IN COMMON IN C

```

```

C CALL CONVER(CC,N)
C GENERATE THE SIMPSON MULTIPLIERS AND STORE THEM IN HELP COMMON
C CALL SIMSON
C GENERATE THE X,S POWER FOR SUBROUTINE FUNCT, STORE THEM IN HELP
C COMMON ARRAY
C CALL MULTI-(X2MAX-X2MIN+N)
C
C DEFINE THE INPUT DATA FOR SUBROUTINE MPOPT
C
C ETA(1)=1.0-12
C ETA(2)=TOL
C ETA(3)=1.0-24
C ETA(4)=1.0-24
C MODE=1
C UMIN=0.0
C
C WRITE THE INTERMEDIATE RESULTS YOU HAVE OBTAINED SO FAR
C
C IF(KPRINT.EQ.0) GO TO 2
C
C WRITE (6,34) N
C WRITE (6,36) X2MAX-X2MIN
C WRITE (6,37) (CC(I),I=1,4)
C IF(N.GT.4) WRITE (6,22) (CC(I),I=5,N)
C WRITE (6,38) (CC(I),I=1,4)
C IF(N.GT.4) WRITE (6,22) (CC(I),I=5,N)
C WRITE (6,39) (ETA(I),I=1,4)
C CONTINUE
46 C FIND-A-STARTING-POINT FOR SUBROUTINE MPOPT TO START THE OPTIMIZATION ALGORITHM
C
C IF(KSTART.EQ.0) GO TO 16
C IF(KSTART.EQ.4) WRITE (6,44)
C CALL START(X2MAX-X2MIN,AL,KSTART,CC,N,KPRINT,UMIN,MODE,MAXFN,ETA)
C IF(INFAIL.EQ.0) GO TO 9
C
C PRINT THE STARTING VALUES
C
C IF (KPRINT.EQ.0) GO TO 7
C GO TO (3,4,5,6), KSTART
C 3   WRITE (6,40)
C 4   WRITE (6,41) (AL(I),I=1,4)
C 5   IF (N.GT.4) WRITE (6,22) (AL(I),I=5,N)
C 6   GO TO 7
C 7   WRITE (6,42) (AL(I),I=1,4)
C 8   IF (N.GT.4) WRITE (6,22) (AL(I),I=5,N)
C 9   WRITE (6,43) (AL(I),I=1,4)
C 10  IF (N.GT.4) WRITE (6,22) (AL(I),I=5,N)
C 11  WRITE (6,44) (AL(I),I=1,4)
C 12  IF (N.GT.4) WRITE (6,22) (AL(I),I=5,N)
C 13  GO TO 7
C 14  IF (N.GT.4) WRITE (6,22) (AL(I),I=5,N)
C 15  CONTINUE
C 16  RANGE=XMAX-XMIN
C 17  C.... CHANGE STARTING VALUES TO 0-1 DOMAIN FOR KSTART=0

```


ORIGINAL PAGE IS
OF POOR QUALITY

```

SUBROUTINE MFOPT (X,NDIM,ETA,EST,MAX,MODE,IPRINT)
C IMPLICIT REAL*8 (A-H,O-Z)
C REALK KTB,IPRINT
C COMMON /FAIL/ NFAIL
C DIMENSION /X,Y/(*),P1(*),P2(*),Y1(*),Y2(*),H1(*),H2(*)
C ... 1(10),* Y1(10), P1(10), P2(10), Y2(10), H1(10), H2(10)
C EXTERNAL FUNCT
C KRST=0
C KTB=0
C FLAG=0
C I=0
C N1=NDIM+1
C N2=NDIM+2
C NUMF=0
C IER=0
C DO 1 I=1,N1
C X1(I)=X(I)
C X2(I)=X(I)
C 1 CONTINUE
C CALL FUNCT (NDIM,X1,F1,GG,RR)
C NUMF=NUMF+1
C DO 2 I=1,NDIM
C X2(I)=X1(I)
C G2(I)=G1(I)
C H2(I)=G1(I)
C 2 CONTINUE
C F2=F1
C X2(N2)=X1(N2)
C X2(N1)=X1(N1)
C 3 CONTINUE
C EPS=ETA(4)
C CALL LINES (FUNCT,X2,H,RO,NDIM,F2,G2,NUMF,IER,EST,RR)
C IF (NFAIL.EQ.1) RETURN
C IF (IER.NE.0) GO TO 30
C DO 4 I=1,N1
C BIGU(I)=X2(I)
C ALFA(I)=X2(I)
C 4 CONTINUE
C RO=-RO
C GG=0.
C DO 5 I=1,NDIM
C GG=GG+G2(I)*G2(I)
C 5 CONTINUE
C GG=SQR(GG)
C IF (IPRINT.EQ.0) GO TO 7
C IF (MOD(KTB,10).NE.0) GO TO 8
C CALL OUTP (X2,F2,H,NDIM,GG,NUMF,RR)
C KTB=KTB+1
C DO 9 I=1,N1
C DO 8 J=1,N1
C P(I,J)=0.
C 8 CONTINUE
C P(I,I)=1.
C 9 CONTINUE
C 10 CONTINUE
C PRINT*,KOUNT
C KOUNT=0
C KOUNT=KOUNT+1
C 11 DO 12 I=1,NDIM
C Y(I)=G2(I)
C PRINT*,GOT BY A1
C 12 Y(N2)=F2

```

```

      V=0.
      DO 13 I=1,NDIM
      V=V+X2(I)*G2(I)
      PRINT*, GOT BY A2
13    CONTINUE

      C     14   I=1,N1
      Y=A=0.
      DO 14 I=1,N1
      YAYA+Y
      PRINT*, GOT BY A3
14    CONTINUE
      YAYA=Y
      BIGV(KOUNT)=V
      DO 15 I=1,N1
      FY(I)=0
      PE(I)=P(I,KOUNT)
      DO 15 J=1,N1
      FY(I)=FY(I)+P(J,I)*Y(J)
      PRINT*- GOT BY A4
      SPY=PY(KOUNT)
      IF (ABS(FY))>SPY(LT,ETA(3)) GO TO 31
      IF (FY(KOUNT))=PY(KOUNT)-1.
      DO 16 I=1,N1
      J=1,N1
      PY(I,J)=P(I,J)-PE(I,J)*PY(J)/EFY
      PRINT*, GOT BY A5
      DO 17 I=1,N1
      ALFA(I)=ALFA(I)+P(I,J)*BIGV(J)
      DO 17 J=1,N1
      PRNTL* GOT BY A6
      DEL=0.
      DO 18 I=1,NDIM
      DEL=DEL+G2(I)*(X2(I)-ALFA(I))
      PRINT*, GOT BY A7
18    CONTINUE
      IF (ABS(DEL)>ETAE(4)) GO TO 19
      IF (IFLAG.EQ.1) RETURN
      IFLAG=1
      GO TO 31
19    IFLAG=0
      DO 20 I=1,N1
      HLL=X2(I)-ALFA(I)
      PRINT*, GOT BY A8
      CONTINUE
      DO 21 I=1,NDIM
      X1(I)=X2(I)
      G1(I)=G2(I)
      PRINT*, GOT BY A9
      CONTINUE
21    IF (DEL.GT.0) H(I)=-H(I)
      PRINT*, GOT BY A10
      CALL LINES (FUNC,X2,H,RD,NDIM,F2,G2,NUMF,IER,EPS,EST,RR)
      IF (NFAIL.EQ.1) RETURN
      IF (IER.NE.0) GO TO 30
      PRINT*, GOT BY A12
      IF (DEL.GT.0) RD=RD
      IF (DEL.GT.0) RD=-RD

```

```

      PRINT*, GOT BY 4
      GG=0.
      DO 22 I=1,NDIM
        GG=GG+G2(I)*XG2(I)
        PRINT*, GOT BY A15,
        COUNT=SDR(GG),
        KOUNT=KOUNT+1
      22 IF (IPRINT,EQ;0) GO TO 23
      IF (MOD,KTB-EPRINT,NE;0) GO TO 23
      C PRINT*, GOT BY S
      C CALL OUT2(XG2,F,M,NDIM,GG,NUMF,RR)
      C CONTINUE
      KTB=KTB+1
      C PRINT*, GOT BY HA
      C PRINT*, GOT BY MAX-GO TO 30
      C NSOL=0
      DO 24 I=1,NDIM
        IE=(ABS(RRI1)-GT,ETA(2)).I. NSOL=1
        PRINT*, GOT BY HC
        CONTINUE
      24 C PRINT*, GOT BY HD'
        PRINT*, GOT BY HD'
        IF (NSOL,NE;0) GO TO 26
        C PRINT*, GOT BY HE
        GO TO 29
      25 C PRINT*, GOT BY HF'
        IE=(GG,LL,FFA(111),OR,(M+GI+MAX)).I. GO TO 26
        PRINT*, GOT BY HG'
        PRINT*, GOT BY HH'
        PRINT*, GOT BY HI'
        PRINT*, GOT BY MI'
        IF (IPRINT,EQ;0) GO TO 27
        C PRINT*, GOT BY HJ
        WRITE(*,601) J
        PRINT*, GOT BY T
        CALL OUTP(X2,F2,M,NDIM,GG,NUMF,RR)
      51 C PRINT*, GOT BY J
      26 DO 28 I=1,NDIM
        XLI=X2(I)
      27 CONTINUE
      EST=F2
      NFAIL=0
      RETURN
      28 CONTINUE
      29 CONTINUE
      30 PRINT*, GOT BY JA
      PRINT*, GOT BY JA
      IF (KOUNT,LE;N1) GO TO 11
      C PRINT*, GOT BY JB
      GO TO 10
      C PRINT*, GOT BY JC
      PRINT 34, IER
      31 KRS1=KRS1+1
      IF (KRS1,GT;10) NFAIL=1
      IF (NFAIL,GT;10) RETURN
      DO 32 I=1,NDIM
        X1(I)=X2(I)
      42 G1(I)=G2(I)

```

```

      32      CONTINUE
      F1=F2
      X1(N2)=X(N2)
      X1(N1)=X(N1)
      X2(N2)=X(N2)
      X2(N1)=X(N1)
      GO TO 3
      C
      C 33  FORMAT ('/SOLUTION FOUND', //,1X, THE PROGRAM HAS FAILED---IER = ',I2)
      END

      C
      C SUBROUTINE OUTP (XNEW,FQ,KOUNT,N1,GG,NUMF,R)
      C IMPLICIT REAL*8 (A-H,O-Z)
      C DIMENSION XNEW(*), R(*)
      C WRITE (*,66) KOUNT,NUMF,GG,FQ+(XNEW(1)+I=1+4)*R(I)+I=1+4)
      C IF (N1=3) RETURN
      NN=N1-3
      GO TO (1,2,3,4,5), NN
      1   RETURN
      2   WRITE (6,7) XNEW(5),R(5)
      3   WRITE (6,8) (XNEW(I),I=5,6),(R(I),I=5,6)
      4   RETURN
      5   WRITE (6,9) (XNEW(I),I=5,7),(R(I),I=5,7)
      6   RETURN
      7   WRITE (6,10) (XNEW(I),I=5,8),(R(I),I=5,8)
      8   RETURN
      C
      C 52  FORMAT (1X,I3,I4,6E14.5,4E10.3)
      C 52  FORMAT (36X,E14.5,4X,E10.3)
      C 52  FORMAT (36X,2E14.5,28X,2E10.3)
      C 52  FORMAT (36X,3E14.5,14X,3E10.3)
      C 52  FORMAT (36X,4E14.5,4E10.3)
      C 52  END

      C
      C SUBROUTINE LINES (FUNCT,X,H,AMBLA,N,F,G,NUMF,IER,EPS,EST,RR)
      C IMPLICIT REAL*8 (A-H,O-Z)
      C REAL*8 Z,DY
      C COMMON /FAIL/NFAIL
      C DIMENSION H(*), X(*), G(*), RR(*)
      C DERO=0
      C DY=0
      C HNRM=0.
      C GNRH=0.
      DO 1 J=1,N
      C HNRM=HNRM+ABS(H(J))
      C GNRH=GNRH+ABS(G(J))
      C DY=D+H(J)*G(J)
      C PRINT*, GOF_BY_B1'
      C CONTINUE
      C IF (DY) 2,31,31
      C 2   PRINT*, GOF_BY_B2'
      C 3   IF (HNRM/GNRH-EPS) -31+31+3
      C 2   PRINT*, GOF_BY_B3'
      C 3   IF (F-Y)
      C 2   ALFA=2.*EST-F)/DY
      C 3   IF (X(N1),GT,0.) ALFA=X(N+1)*ALFA/2.
      C 2   PRINT*, GOF_BY_B4'

```

```

1 MRAA-1
2 IF (ALFA) 3,6,4
3 PRINT*, GOT BY B5
4 IF (ALFA-AMUDA) 5,6,6
5 PRINT*, GOT BY B6
6 AMUDA=ALFA
7 ALFA=0+
8 DO 9 I=1,N
9 X(I)=X(I)+AMUDA*X(I)
C PRINT*, GOT BY B7
CONTINUE
7 FX=FY
8 DX=DY
C PRINT*, GOT BY B8
C CALL FUNCT,(N*X,F,G,RR)
C PRINT*, GOT BY B9
IF (NFAIL.EQ.1) RETURN
C PRINT*, GOT BY B10
NUMF=NUMFL
IF (F.LT.FX) RETURN
C PRINT*, GOT BY B11
FY=F
DO 9 I=1,N
9 DY=DY+G(I)*XH(I)
C PRINT*, GOT BY B12
CONTINUE
C PRINT*, GOT BY B13
IF (DY) 10,30,13
C PRINT*, GOT BY B14
10 . . .
11 . . .
12 . . .
13 . . .
14 . . .
15 . . .
53 . . .
16 . . .
17 . . .
18 . . .
19 . . .
20 . . .
21 . . .
22 . . .
23 . . .
24 . . .
25 . . .
26 . . .
27 . . .
28 . . .
29 . . .
30 . . .
31 . . .
32 . . .
33 . . .
34 . . .
35 . . .
36 . . .
37 . . .
38 . . .
39 . . .
40 . . .
41 . . .
42 . . .

```

ORIGINAL PAGE IS
OF POOR QUALITY

```
1 IF (F-FY) .GT. 1E-11 THEN
2   DALFA=0.
3 DO 13 I=1,N
4   DALFA=DALFA+G(I)*H(I)
5 CONTINUE
6 IF (DALFA).LT.24.27.27 THEN
7 IF (F-FY).GT.25.27 GO TO 29
8 IF (DX-DALFA).GT.26.30.26 GO TO 29
9 FX=F
10 DX=DALFA
11 T=ALFA
12 AMBDA=ALFA
13 GO TO 14
14 IF (FY-F).GT.29.28.29 GO TO 29
15 IF (DY-DALFA).GT.29.30.29 GO TO 29
16 FY=F
17 DY=DALFA
18 AMBDA=AMBDA-ALFA
19 GO TO 13
20 AMBDA=AMBDA-ALFA
21 RETURN
22 CONTINUE
23 IF (DY.GE.0.) IER=-2
24 IF (GNRM.LE.1.E-10) GO TO 32
25 IF (CHNRM/GNRM.LE.EPS) IER=-3
26 CONTINUE
27 IF (DALFA.LT.0.) IER=-1
28 IF FAIL=.1.
29 WRITE(6,33)
30 FORMAT(//,1X,' THE PROGRAM HAS FAILED')
31 RETURN
32 C.... ABOVE LINE CHANGED FROM TEXT
33 C.... SUBROUTINE FUNCT (N,AL,U,GRAD,RR)
34 C.... IMPLICIT REAL*8 (A-H,O-Z)
35 C.... THIS SUBROUTINE IS USED TO CALCULATE THE OPTIMIZATION AND THE
36 C.... GRADIENT AT ANY GIVEN POINT FOR SUBROUTINE P0PT
37 C.... DIMENSION AL(*),GRAD(*),SUM(17),RR(*)
38 C.... COMMON /FAIL/NFAIL,
39 C.... COMMON /HELP/S(101),XX(16,101),C(8),H
40 C.... END
41 C.... N21=2*N+1
42 C.... ZERO=0.0
43 C.... DO 1 I=1,N21
44 C.... SUM(I)=0.0
45 C.... PRINT*, ' GOT BY C1'
46 C.... CONTINUE
47 C.... DO 4 I=L,M
48 C.... SZ=ZERO
49 C.... DO 3 K=1,N
50 C.... SZ=SZ+AL(K)**XX(K,I)
51 C.... PRINT*, ' GOT BY C2'
52 C.... CONTINUE
53 C.... IF (SZ.GT.74.) GO TO 9
54 C.... PRINT*, ' GOT BY C3'
55 C.... SSEP=S21S11
56 C.... SUM(1)=SUM(1)+SS
```

```

80--J=2*N21
SUM(J)=SUM(J)+XX(J-1,I)*X33
PRINT*, GOT BY C4
CONTINUE
C4      SUM(I)=SUM(I)/SUM(J)
      PRINT*, GOT BY C5
CONTINUE
C5      U=0.0
      DO 6 I=1,N
         RR(I)=SUM(I+1)-C(I))/C(I)
         U=U+RR(I)*RR(I)
      PRINT*, GOT BY C6
      C6      CONTINUE
      C6      DO 3 K=1,N
         RAO(K)=0.0
      DO 7 J=1,N
         GRAD(K)=GRAD(K)+(SUM(J+K+1)-SUM(J+1))*RR(J)/C(J)
      PRINT*, GOT BY C7
      C7      CONTINUE
      C7      GRAD(K)=GRAD(K)*X2
      PRINT*, GOT BY C8
      C8      CONTINUE
      C8      RETURN
      PRINT*, GOT BY C9
      C9      CONTINUE
      AA=S2/J2
      ZERO=ZERO-AA
      GO TO 2
      PRINT*, GOT BY C10
      C10      CONTINUE
      END
      C11      PRINT*, GOT BY C11
      END
      C11      SUBROUTINE START(XMAX,XMIN,ALAMDA,KSTART,CC,NL,IPRINT,UMIN,MODE,M
      C11      IMPLICIT REAL*8 (A-H,O-Z)
      C11      THIS SUBROUTINE IS USED TO FIND A REASONABLE STARTING POINT FOR
      C11      SUBROUTINE MPOPT
      C11      DIMENSION CC(*), ETA(*)
      C11      DIMENSION ALAMDA(*), X(10), Y(10), W(10,10)
      C11      COMMON/HELP/S(10), XX(16,10), C(8), M
      C11      ABOVE LINE CHANGED FROM TEXT
      C11      COMMON /FAIL/NFAIL
      C11      GO TO (3,1,5,26), KSTART
      C11      1      CONTINUE
      C11      2      NEAL=0
      C11      3      DO 2 I=1,NL
      C11      4      ALAMDA(I)=0.0
      C11      5      CONTINUE
      C11      6      NFAIL=0
      C11      7      ALAMDA(1)=CC(1)/CC(2)
      C11      8      ALAMDA(2)=CC(2)/CC(2)
      C11      9      DO 4 I=3,NL
      C11      10      ALAMDA(I)=0.0
      C11      11      CONTINUE
      C11      12      RETURN
      C11      13      CONTINUE
      C11      14      3
      C11      15      4
      C11      16      5
      C11      17      6
      C11      18      7
      C11      19      8
      C11      20      9
      C11      21      10
      C11      22      11
      C11      23      12
      C11      24      13
      C11      25      14
      C11      26      15
      C11      27      16
      C11      28      17
      C11      29      18
      C11      30      19
      C11      31      20
      C11      32      21
      C11      33      22
      C11      34      23
      C11      35      24
      C11      36      25
      C11      37      26
      C11      38      27
      C11      39      28
      C11      40      29
      C11      41      30
      C11      42      31
      C11      43      32
      C11      44      33
      C11      45      34
      C11      46      35
      C11      47      36
      C11      48      37
      C11      49      38
      C11      50      39
      C11      51      40
      C11      52      41
      C11      53      42
      C11      54      43
      C11      55      44
      C11      56      45
      C11      57      46
      C11      58      47
      C11      59      48
      C11      60      49
      C11      61      50
      C11      62      51
      C11      63      52
      C11      64      53
      C11      65      54
      C11      66      55
      C11      67      56
      C11      68      57
      C11      69      58
      C11      70      59
      C11      71      60
      C11      72      61
      C11      73      62
      C11      74      63
      C11      75      64
      C11      76      65
      C11      77      66
      C11      78      67
      C11      79      68
      C11      80      69
      C11      81      70
      C11      82      71
      C11      83      72
      C11      84      73
      C11      85      74
      C11      86      75
      C11      87      76
      C11      88      77
      C11      89      78
      C11      90      79
      C11      91      80
      C11      92      81
      C11      93      82
      C11      94      83
      C11      95      84
      C11      96      85
      C11      97      86
      C11      98      87
      C11      99      88
      C11      100      89
      C11      101      90
      C11      102      91
      C11      103      92
      C11      104      93
      C11      105      94
      C11      106      95
      C11      107      96
      C11      108      97
      C11      109      98
      C11      110      99
      C11      111      100
      C11      112      101
      C11      113      102
      C11      114      103
      C11      115      104
      C11      116      105
      C11      117      106
      C11      118      107
      C11      119      108
      C11      120      109
      C11      121      110
      C11      122      111
      C11      123      112
      C11      124      113
      C11      125      114
      C11      126      115
      C11      127      116
      C11      128      117
      C11      129      118
      C11      130      119
      C11      131      120
      C11      132      121
      C11      133      122
      C11      134      123
      C11      135      124
      C11      136      125
      C11      137      126
      C11      138      127
      C11      139      128
      C11      140      129
      C11      141      130
      C11      142      131
      C11      143      132
      C11      144      133
      C11      145      134
      C11      146      135
      C11      147      136
      C11      148      137
      C11      149      138
      C11      150      139
      C11      151      140
      C11      152      141
      C11      153      142
      C11      154      143
      C11      155      144
      C11      156      145
      C11      157      146
      C11      158      147
      C11      159      148
      C11      160      149
      C11      161      150
      C11      162      151
      C11      163      152
      C11      164      153
      C11      165      154
      C11      166      155
      C11      167      156
      C11      168      157
      C11      169      158
      C11      170      159
      C11      171      160
      C11      172      161
      C11      173      162
      C11      174      163
      C11      175      164
      C11      176      165
      C11      177      166
      C11      178      167
      C11      179      168
      C11      180      169
      C11      181      170
      C11      182      171
      C11      183      172
      C11      184      173
      C11      185      174
      C11      186      175
      C11      187      176
      C11      188      177
      C11      189      178
      C11      190      179
      C11      191      180
      C11      192      181
      C11      193      182
      C11      194      183
      C11      195      184
      C11      196      185
      C11      197      186
      C11      198      187
      C11      199      188
      C11      200      189
      C11      201      190
      C11      202      191
      C11      203      192
      C11      204      193
      C11      205      194
      C11      206      195
      C11      207      196
      C11      208      197
      C11      209      198
      C11      210      199
      C11      211      200
      C11      212      201
      C11      213      202
      C11      214      203
      C11      215      204
      C11      216      205
      C11      217      206
      C11      218      207
      C11      219      208
      C11      220      209
      C11      221      210
      C11      222      211
      C11      223      212
      C11      224      213
      C11      225      214
      C11      226      215
      C11      227      216
      C11      228      217
      C11      229      218
      C11      230      219
      C11      231      220
      C11      232      221
      C11      233      222
      C11      234      223
      C11      235      224
      C11      236      225
      C11      237      226
      C11      238      227
      C11      239      228
      C11      240      229
      C11      241      230
      C11      242      231
      C11      243      232
      C11      244      233
      C11      245      234
      C11      246      235
      C11      247      236
      C11      248      237
      C11      249      238
      C11      250      239
      C11      251      240
      C11      252      241
      C11      253      242
      C11      254      243
      C11      255      244
      C11      256      245
      C11      257      246
      C11      258      247
      C11      259      248
      C11      260      249
      C11      261      250
      C11      262      251
      C11      263      252
      C11      264      253
      C11      265      254
      C11      266      255
      C11      267      256
      C11      268      257
      C11      269      258
      C11      270      259
      C11      271      260
      C11      272      261
      C11      273      262
      C11      274      263
      C11      275      264
      C11      276      265
      C11      277      266
      C11      278      267
      C11      279      268
      C11      280      269
      C11      281      270
      C11      282      271
      C11      283      272
      C11      284      273
      C11      285      274
      C11      286      275
      C11      287      276
      C11      288      277
      C11      289      278
      C11      290      279
      C11      291      280
      C11      292      281
      C11      293      282
      C11      294      283
      C11      295      284
      C11      296      285
      C11      297      286
      C11      298      287
      C11      299      288
      C11      300      289
      C11      301      290
      C11      302      291
      C11      303      292
      C11      304      293
      C11      305      294
      C11      306      295
      C11      307      296
      C11      308      297
      C11      309      298
      C11      310      299
      C11      311      300
      C11      312      301
      C11      313      302
      C11      314      303
      C11      315      304
      C11      316      305
      C11      317      306
      C11      318      307
      C11      319      308
      C11      320      309
      C11      321      310
      C11      322      311
      C11      323      312
      C11      324      313
      C11      325      314
      C11      326      315
      C11      327      316
      C11      328      317
      C11      329      318
      C11      330      319
      C11      331      320
      C11      332      321
      C11      333      322
      C11      334      323
      C11      335      324
      C11      336      325
      C11      337      326
      C11      338      327
      C11      339      328
      C11      340      329
      C11      341      330
      C11      342      331
      C11      343      332
      C11      344      333
      C11      345      334
      C11      346      335
      C11      347      336
      C11      348      337
      C11      349      338
      C11      350      339
      C11      351      340
      C11      352      341
      C11      353      342
      C11      354      343
      C11      355      344
      C11      356      345
      C11      357      346
      C11      358      347
      C11      359      348
      C11      360      349
      C11      361      350
      C11      362      351
      C11      363      352
      C11      364      353
      C11      365      354
      C11      366      355
      C11      367      356
      C11      368      357
      C11      369      358
      C11      370      359
      C11      371      360
      C11      372      361
      C11      373      362
      C11      374      363
      C11      375      364
      C11      376      365
      C11      377      366
      C11      378      367
      C11      379      368
      C11      380      369
      C11      381      370
      C11      382      371
      C11      383      372
      C11      384      373
      C11      385      374
      C11      386      375
      C11      387      376
      C11      388      377
      C11      389      378
      C11      390      379
      C11      391      380
      C11      392      381
      C11      393      382
      C11      394      383
      C11      395      384
      C11      396      385
      C11      397      386
      C11      398      387
      C11      399      388
      C11      400      389
      C11      401      390
      C11      402      391
      C11      403      392
      C11      404      393
      C11      405      394
      C11      406      395
      C11      407      396
      C11      408      397
      C11      409      398
      C11      410      399
      C11      411      400
      C11      412      401
      C11      413      402
      C11      414      403
      C11      415      404
      C11      416      405
      C11      417      406
      C11      418      407
      C11      419      408
      C11      420      409
      C11      421      410
      C11      422      411
      C11      423      412
      C11      424      413
      C11      425      414
      C11      426      415
      C11      427      416
      C11      428      417
      C11      429      418
      C11      430      419
      C11      431      420
      C11      432      421
      C11      433      422
      C11      434      423
      C11      435      424
      C11      436      425
      C11      437      426
      C11      438      427
      C11      439      428
      C11      440      429
      C11      441      430
      C11      442      431
      C11      443      432
      C11      444      433
      C11      445      434
      C11      446      435
      C11      447      436
      C11      448      437
      C11      449      438
      C11      450      439
      C11      451      440
      C11      452      441
      C11      453      442
      C11      454      443
      C11      455      444
      C11      456      445
      C11      457      446
      C11      458      447
      C11      459      448
      C11      460      449
      C11      461      450
      C11      462      451
      C11      463      452
      C11      464      453
      C11      465      454
      C11      466      455
      C11      467      456
      C11      468      457
      C11      469      458
      C11      470      459
      C11      471      460
      C11      472      461
      C11      473      462
      C11      474      463
      C11      475      464
      C11      476      465
      C11      477      466
      C11      478      467
      C11      479      468
      C11      480      469
      C11      481      470
      C11      482      471
      C11      483      472
      C11      484      473
      C11      485      474
      C11      486      475
      C11      487      476
      C11      488      477
      C11      489      478
      C11      490      479
      C11      491      480
      C11      492      481
      C11      493      482
      C11      494      483
      C11      495      484
      C11      496      485
      C11      497      486
      C11      498      487
      C11      499      488
      C11      500      489
      C11      501      490
      C11      502      491
      C11      503      492
      C11      504      493
      C11      505      494
      C11      506      495
      C11      507      496
      C11      508      497
      C11      509      498
      C11      510      499
      C11      511      500
      C11      512      501
      C11      513      502
      C11      514      503
      C11      515      504
      C11      516      505
      C11      517      506
      C11      518      507
      C11      519      508
      C11      520      509
      C11      521      510
      C11      522      511
      C11      523      512
      C11      524      513
      C11      525      514
      C11      526      515
      C11      527      516
      C11      528      517
      C11      529      518
      C11      530      519
      C11      531      520
      C11      532      521
      C11      533      522
      C11      534      523
      C11      535      524
      C11      536      525
      C11      537      526
      C11      538      527
      C11      539      528
      C11      540      529
      C11      541      530
      C11      542      531
      C11      543      532
      C11      544      533
      C11      545      534
      C11      546      535
      C11      547      536
      C11      548      537
      C11      549      538
      C11      550      539
      C11      551      540
      C11      552      541
      C11      553      542
      C11      554      543
      C11      555      544
      C11      556      545
      C11      557      546
      C11      558      547
      C11      559      548
      C11      560      549
      C11      561      550
      C11      562      551
      C11      563      552
      C11      564      553
      C11      565      554
      C11      566      555
      C11      567      556
      C11      568      557
      C11      569      558
      C11      570      559
      C11      571      560
      C11      572      561
      C11      573      562
      C11      574      563
      C11      575      564
      C11      576      565
      C11      577      566
      C11      578      567
      C11      579      568
      C11      580      569
      C11      581      570
      C11      582      571
      C11      583      572
      C11      584      573
      C11      585      574
      C11      586      575
      C11      587      576
      C11      588      577
      C11      589      578
      C11      590      579
      C11      591      580
      C11      592      581
      C11      593      582
      C11      594      583
      C11      595      584
      C11      596      585
      C11      597      586
      C11      598      587
      C11      599      588
      C11      600      589
      C11      601      590
      C11      602      591
      C11      603      592
      C11      604      593
      C11      605      594
      C11      606      595
      C11      607      596
      C11      608      597
      C11      609      598
      C11      610      599
      C11      611      600
      C11      612      601
      C11      613      602
      C11      614      603
      C11      615      604
      C11      616      605
      C11      617      606
      C11      618      607
      C11      619      608
      C11      620      609
      C11      621      610
      C11      622      611
      C11      623      612
      C11      624      613
      C11      625      614
      C11      626      615
      C11      627      616
      C11      628      617
      C11      629      618
      C11      630      619
      C11      631      620
      C11      632      621
      C11      633      622
      C11      634      623
      C11      635      624
      C11      636      625
      C11      637      626
      C11      638      627
      C11      639      628
      C11      640      629
      C11      641      630
      C11      642      631
      C11      643      632
      C11      644      633
      C11      645      634
      C11      646      635
      C11      647      636
      C11      648      637
      C11      649      638
      C11      650      639
      C11      651      640
      C11      652      641
      C11      653      642
      C11      654      643
      C11      655      644
      C11      656      645
      C11      657      646
      C11      658      647
      C11      659      648
      C11      660      649
      C11      661      650
      C11      662      651
      C11      663      652
      C11      664      653
      C11      665      654
      C11      666      655
      C11      667      656
      C11      668      657
      C11      669      658
      C11      670      659
      C11      671      660
      C11      672      661
      C11      673      662
      C11      674      663
      C11      675      664
      C11      676      665
      C11      677      666
      C11      678      667
      C11      679      668
      C11      680      669
      C11      681      670
      C11      682      671
      C11      683      672
      C11      684      673
      C11      685      674
      C11      686      675
      C11      687      676
      C11      688      677
      C11      689      678
      C11      690      679
      C11      691      680
      C11      692      681
      C11      693      682
      C11      694      683
      C11      695      684
      C11      696      685
      C11      697      686
      C11      698      687
      C11      699      688
      C11      700      689
      C11      701      690
      C11      702      691
      C11      703      692
      C11      704      693
      C11      705      694
      C11      706      695
      C11      707      696
      C11      708      697
      C11      709      698
      C11      710      699
      C11      711      700
      C11      712      701
      C11      713      702
      C11      714      703
      C11      715      704
      C11      716      705
      C11      717      706
      C11      718      707
      C11      719      708
      C11      720      709
      C11      721      710
      C11      722      711
      C11      723      712
      C11      724      713
      C11      725      714
      C11      726      715
      C11      727      716
      C11      728      717
      C11      729      718
      C11      730      719
      C11      731      720
      C11      732      721
      C11      733      722
      C11      734      723
      C11      735      724
      C11      736      725
      C11      737      726
      C11     
```

```

      NF=11
      NNN=NNN/2
      NNP1=NNN/2
      NP1=NL+1
      DELTA=(XMAX-XMIN)/FLOAT(NL)
      CONTINUE
      6   IF (NNN.EQ.NL) GO TO 19
      W(1,1)=1
      W(1,2)=1
      DO 7 I=2,NL,2
      W(1,I)=2
      W(1,I)=2
      W(1,I)=4
      7   CONTINUE
      8   IF (NL.EQ.2) GO TO 9
      NM1=NL-1
      DO 9 I=3,NM1,2
      W(1,I)=2
      W(1,I)=2
      CONTINUE
      9   DO 10 J=1,NP1
      10  DO 11 I=2,NP1
      W(1,J)=W(I-1,J)*X(J)
      Y(I)=3./DELTA
      DO 12 I=1,NL
      Y(I+1)=C(I)*Y(I)
      12  CONTINUE
      CALL SOLVE (W,Y,XID,NP1,10)
      13  CONTINUE
      DO 13 I=1,NP1
      W(1,I)=0.
      13  CONTINUE
      14  DO 14 I=1,NP1
      Y(I)=LE.O.O) Y(I)=.0002
      14  CONTINUE
      DO 15 I=1,NP1
      Y(I)= ALOG(Y(I))
      15  CONTINUE
      DO 16 I=1,NP1
      W(1,I)=I.
      16  CONTINUE
      DO 17 I=2,NP1
      W(1,I)=W(I-1,NP1)*X(I)
      17  CALL SOLVE (W,Y,XID,NP1,10)
      DO 18 I=1,NL
      ALAMDA(I)=Y(I+1)
      18  CONTINUE
      RETURN
      19  CONTINUE
      R(1)=3./8.
      R(4)=3./8.
      R(2)=9./8.
      R(3)=9./8.
      IF (NL.EQ.3) GO TO 22
      R(NL+1)=1./3.
      R(4)=R(4)+1./3.
      DO 20 I=5,NL,2
      R(I)=4./3.
      20  CONTINUE
      IF (NL.EQ.5) GO TO 22
      NS=NL-1
      DO 21 I=6,NS,2
      R(I)=2./3.
      21

```

```

21 60NTINME
22 CONTINUE
DO 23 I=1,NP1
  Y(I,I)=R(I)
23 CONTINUE
DO 24 J=1,NP1
  DO 24 J=1,NP1
    Y(I,J)=Y(I,J)*X(J)
  Y(I,J)=1./DELT
  DO 25 I=1,NL
    Y(I,J)=C(I)*Y(I,J)
25 CONTINUE
CALL SOLVE (W,Y,XID,NP1,10)
CONT TO 12
CONTINUE
N=2
ALAMDA(2)=-5/CC(2)
ALAMDA(1)=CC(1)/CC(2)
NFAIL=0
27 CONTINUE
ALAMDA(N+1)=2.0
C PRINT*, GOT BY A'
CALL MPOPT (ALAMDA,N,ETA,UMIN,MAXFN,MODE,IPRINT)
C PRINT*, GOT BY B'
IF (NFAIL.EQ.1) RETURN
IF (N-ED-NL).RETURN
ALAMDA(N+1)=0.0
N=N+1
GO TO 27
END

```

SUBROUTINE SOLVE (A,X,XID,N,NA)

```

IMPLICIT REAL*8 (A-H,O-Z)
DIMENSION A(NA,*), X(*)
D=0.
DATA DIV/ .693147181 /
DO 6 I=1,N
  AA=0.
  DO 1 J=1,N
    AB=ABS(A(J,I))
    IF (AB.GE.AA) GO TO 1
    AA=AB
  1 CONTINUE
  K=J
  AA=AB
  DO 7 CONTINUE
    IF (K.EQ.I) GO TO 7
    DO 2 J=1,N
      AB=A(J,J)
      A(I,J)=A(K,J)
      A(K,J)=AB
    2 CONTINUE
    AB=X(I)
    X(I)=X(K)
    X(K)=AB
  7 CONTINUE
  DO 8 J=1,N
    AA=-A(J,I)/A(I,I)
    A(J,I)=0.
    DO 4 K=1,N
      A(J,K)=AA*A(K,I)
    4 CONTINUE
  8 CONTINUE
END

```

```

*-----*-----*-----*-----*-----*-----*-----*-----*
5      CONTINUE
6      XID=0/DIV
7      X(N)=X(N)/A(N,N)
8      D0 9  I1=2,N
9      I1=N+1-I1
10     I1=I1+1
11     AA=0.
12     D0 9  J=I1,N
13     X(I1)=(X(I1)-AA)/A
14     CONTINUE
15     X(I1)=(X(I1)-AA)/A
16     CONTINUE
17     RETURN
END

```

```

C   SUBROUTINE SIMSON
C   IMPLICIT REAL*8 (A-H,Q-Z)
C
C   THIS SUBROUTINE IS TO CALCULATE THE SIMPSON MULTIPLIERS
C
C   COMMON /HELP/S(101),XX(14,101),C(8),M
C   ABOVE LINE CHANGED FROM TEXT
C
C.....

```

```

N=1
DO 2 I=3,N,2
S(I)=2
CONTINUE
RETURN
END

```

```
SUBROUTINE MULTI (XMAX,XMIN,N)
IMPLICIT REAL*8 (A-H,O-Z)
```

THIS SUBROUTINE IS USED TO GENERATE THE X,S,POWER FOR SUBROUTINE EINCT

```

      COMMON/HELP/S(101),XXX(16,101),C(8),M
      ABOVE LINE CHANGED FROM TEXT
      DELTA = (XMAX-XMIN)/FLOAT(N-1)
      DO 1 I=1,N
      1 XX(I) = XMIN+FLOAT(I-1)*DELTA
      END
      
```

```
NN=2*N
DO 1 J=2,NN
    XX(J)=XX(J-1,I)*XX(1,I)
CONTINUE
RETURN
```

```
SUBROUTINE CONVER (CM,NL)
C IMPLICIT REAL*8 (A-H,O-Z)
C THIS SUBROUTINE IS TO CALCULATE
C DIMENSION CM(7)
```

```

C---- SUBROUTINE CH(1)
C.... ABOVE LINE CHANGED FROM TEXT
C(1)=CH(1)
IF (NL.EQ.1) RETURN
DO 1 J=2,NL
C(J)=CM(J)-C(1)**J*(~-1.)***J
DO 1 K=1,N
C(J)=C(J)-(-1.)**K*FACT0(J)/(FACT0(K)*C(1)**(K)*C(J-K))
CONTINUE
1 CONTINUE
RETURN
END

SUBROUTINE TRN1 (X1MAX,X1MIN,C,X2MAX,X2MIN,NL)
IMPLICIT REAL*8 (A-H,O-Z)
C---- THIS SUBROUTINE IS USED TO CALCULATE THE MOMENTS FOR THE MODIFIED
C---- LIMITS
C
DIMENSION C(1)
C(1)=C(1)/SCL-X1MIN/SCL+X2MIN
IF (NL.EQ.1) RETURN
DO 1 I=2,NL
C(I)=C(I)*SCL**FLOAT(I)
1 CONTINUE
RETURN
END

59 SUBROUTINE TRN2(X1MAX,X1MIN,X,X2MAX,X2MIN,N)
IMPLICIT REAL*8 (A-H,O-Z)
C---- THIS SUBROUTINE IS AN ALTERNATIVE TO TRN2 (BELOW)
C---- CALCULATES THE LAGRANGIAN MULTIPLIERS FOR A DIFFERENT INTERVAL
C---- DOUBLE PRECISION VERSION
C---- DOUBLE PRECISION S,A,DX(10),FAC,DX1MAX,DX1MIN,DX2MAX,DX2MIN
DIMENSION X(*)
DX1MAX=X1MAX
DX1MIN=X1MIN
DX2MAX=X2MAX
DX2MIN=X2MIN
NP1=N+1
DO 10 I=1, NP1
DX(I)=X(I)
10 DX(I)=DX(I)-DX1MIN/(DX2MAX-DX2MIN)
A=(DX1MAX-DX1MIN)/S
DX(1)=DX(1)-ALOG(S)
DO 11 I=1,N
DX(I)=DX(I)+DX(I+1)*A**I
11 CONTINUE
IF (N.EQ.1) GO TO 6
DO 12 I=2,N
DX(I)=DX(I)-DX(I-1)
12 DO 13 I=J,N
FAC=1.
13 DO 14 K=1,J-2,N
FAC=FAC*FLOAT(K)
14 DO 15 K=K+1,J
FAC=FAC*DBLE(FLOAT(K))
15 CONTINUE
DX(J)=DX(J)+FAC/DBLE(FACT0(J-1))*A**((I-J+1)*DX(I+1))
16 CONTINUE
C4 DX(J)=DX(J)/S**((J-1))

```

```

      CONTINUE
      DO 11 I=1,NPI
      X(I)=0*X(I)
      RETURN
      END

      SUBROUTINE TRN2 (X1MAX,X1MIN,X,X2MAX,X2MIN,N)
C
C THIS SUBROUTINE IS USED TO CALCULATE THE LAGRANGIAN MULTIPLIERS
C AT THE ORIGINAL LIMITS
C
      DIMENSION X(1)
      S=(X1MAX-X1MIN)/(X2MAX-X2MIN)
      A=X2MIN-X1MIN/S
      X(1)=X(1)-ALOG(S)
      DO 1 I=1,N
      X(1)=X(1)+X(I+1)*XXXI
      1  CONTINUE
      IF (N.EQ.1) GO TO 3
      DO 5 J=2,N
      DO 3 I=J,N
      FAC=1
      K=N-J+2
      DO 2 K=KK,I
      FAC=FAC*FLOAT(K)
      2  CONTINUE
      X(J)=X(J)+FAC/FAC*(J-1)*XXXL-JFL*X(I)
      3  CONTINUE
      4  CONTINUE
      X(N+1)=X(N+1)/S***N
      RETURN
      END

      FUNCTION CDF (XMIN,XMAX,XP,AL,N)
C
C IMPLICIT REAL*8 (A-H,O-Z)
C THIS FUNCTION-SUBROUTINE IS TO CALCULATE THE CUMULATIVE-DISTRIBUTION
C FUNCTION AT A GIVEN POINT
C... INPUT
C     XMIN = LOWER BOUND
C     XMAX = UPPER BOUND
C     AL(I) = ARRAY OF PARAMETERS, DIMENSION N
C     N = NUMBER OF PARAMETERS
C
C DIMENSION AL(1)
      IF (XP.LE.XMIN) GO TO 3
      IF (XP.GE.XMAX) GO TO 4
      RANGE=XMAX-XMIN
      Rangen=XP-XMIN
      SS=Rangen/RANGE*S1.
      JSS=(JSS/2)*2+5
      AREA=0.0
      JSM1=JSS-1
      DELTA=Rangen/FLOAT(JSM1)
      DO 1 I=2,JSM1,2
      XMIN=DELTA*I-LRDELTA
      AREA=AREA+4.*ENTRPF(AL,N,X)
      1

```


ORIGINAL PAGE IS
OF POOR QUALITY

| | |
|----------|---------|
| 900.0000 | 45.0000 |
| 53.0000 | 2.3000 |
| 500.0000 | 25.2000 |
| 250.0000 | 12.5000 |
| 150.0000 | -7.5000 |
| 150.0000 | 9.0150 |
| 150.0000 | 75.0000 |
| 250.0000 | 11.2500 |
| 350.0000 | 25.5000 |

**ORIGINAL PAGE IS
OF POOR QUALITY**

File DBAO:[JRANDOM4.CPPR1] (383,942,0) last revised on 23-NOV-1988 11:21, is a 51 block sequential file owned by UIC
 Job RANDOM4-(685)- queued to SYS\$SBPRT-07- 23-NOV-1988- 11:22 by user NETROMPRIU- UIC-F14-tt1- under account 2010ADD-
 started on printer -TTF7: on 23-NOV-1988 11:22 from queue TTF7.

INPUT DATA FOR SUBROUTINE MEP:

INPUT DATA IS PRINTED OUT FOR KDATA =1 ONLY KDATA = 1
INTERMEDIATE OUTPUT EVERY KPRINT (TH) CYCLE KPRINT = 1
NUMBER OF KNOWN FIRST MOMENTS N= 4
HIGHER LIMIT XMAX = 0. 963779301E+01
LOWER LIMIT XMIN = 0. 373349819E+01
FIRST MOMENTS CC(I) = 0. 735451628E+01 0. 370334345E+00 0. 762378196E+00
THE ALLOWED TOLERANCE IN LAGRANGIAN EQUATIONS TOL = 0. 10000000E-05
THE CUMULATIVE DISTRIBUTION REQUIRED AT NXP POINTS. NXP = 0

ORIGINAL PAGE IS
OF POOR QUALITY

INTERMEDIATE RESULTS FOR SUBROUTINE NEP

| NUMBER OF INTEGRATION STATION | | | | M = 31 |
|---|---------------------------|--------------------------|------------------|------------------|
| MODIFIED MAXIMUM AND MINIMUM LIMITS | X2MAX = 0. 100000000E+01 | X2MIN = 0. 000000000E+00 | | |
| MODIFIED MOMENTS ABOUT THE EXPECTED VALUE | CC(1) = 0. 416759124E+00 | C(1) = 0. 372239500E+01 | 0. 297073601E+02 | 0. 324755300E+02 |
| MODIFIED MOMENTS ABOUT THE ORIGIN | C(1) = 0. 416759124E+00 | 216812119E+00 | 0. 121887179E+00 | 0. 774970120E+01 |
| SUBROUTINE MPOPT TOLERANCES | ETA(1) = 0. 100000000E-11 | 0. 100000000E-05 | 0. 100000000E-23 | 0. 100000000E-22 |

NORMAL ASSUMPTION STARTING METHOD

STARTING VALUES AL(1) = 0. 111959940E+02 -0. 134322122E+02 0. 300000000E+00 2. 000000000E+00

| 69 | CYC NO. | NORMGRAD | TOTAL RESIDUALS X(1) | VARIABLES X(3) | | | R(1) | R(2) | RESIDUALE R(3) | R(4) |
|----|---------|-----------------|----------------------|----------------------------|----------------------------|--------------|--------------|------------|----------------|------------|
| | | | | X(2) | X(4) | X(5) | | | | |
| 0 | 2 | 0. 17606E-01 | 0. 23715E-02 | 0. 11222E+02 -0. 13405E+02 | 0. 23839E-01 | 0. 19738E-01 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 1 | 4. 0. 52974E-02 | 0. 22054E-02 | 0. 11262E+02 -0. 13405E+02 | 0. 23839E-01 | 0. 19738E-01 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 2 | 0. 51894E-02 | 0. 22080E-04 | 0. 30751E+01 -0. 77949E+01 | 0. 33858E+00 | 0. 19738E+00 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 3 | 0. 19418E-02 | 0. 92570E-04 | 0. 30751E+01 -0. 77949E+01 | 0. 33858E+00 | 0. 19738E+00 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 4 | 0. 42977E-02 | 0. 31381E-04 | 0. 21444E+02 -0. 49492E+02 | 0. 79107E+02 | 0. 39801E+02 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 5 | 0. 27787E-02 | 0. 32086E-04 | 0. 17631E+02 -0. 47370E+02 | 0. 55144E+02 | 0. 27447E+02 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 6 | 0. 24294E-02 | 0. 18863E-04 | 0. 20061E+02 -0. 56261E+02 | 0. 69356E+02 | 0. 34212E+02 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 7 | 0. 13074E-02 | 0. 10598E-04 | 0. 22892E+02 -0. 67284E+02 | 0. 34353E+02 | 0. 42016E+02 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 8 | 0. 35064E-03 | 0. 10539E-04 | 0. 23238E+02 -0. 68397E+02 | 0. 36281E+02 | 0. 42977E+02 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 9 | 0. 12140E-03 | 0. 36089E-05 | 0. 26844E+02 -0. 79546E+02 | 0. 38742E+02 | 0. 47577E+02 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 10 | 0. 27919E-03 | 0. 25729E-05 | 0. 27017E+02 -0. 80287E+02 | 0. 39929E+02 | 0. 48205E+02 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 11 | 0. 34294E-03 | 0. 12032E-05 | 0. 27481E+02 -0. 81924E+02 | 0. 96306E+02 | 0. 49736E+02 | 0. 210E-01 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 12 | 0. 73 | 0. 14845E-03 | 0. 72443E-06 | 0. 28685E+02 -0. 85797E+02 | 0. 10725E+03 | 0. 51594E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 13 | 0. 235 | 0. 43064E-03 | 0. 71197E-06 | 0. 28914E+02 -0. 86679E+02 | 0. 10830E+03 | 0. 52246E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 14 | 0. 227 | 0. 34003E-03 | 0. 47343E-06 | 0. 36093E+02 -0. 90214E+02 | 0. 11405E+03 | 0. 52381E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 15 | 0. 229 | 0. 34003E-03 | 0. 40703E-06 | 0. 34528E+02 -0. 90180E+02 | 0. 10818E+03 | 0. 52381E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 16 | 0. 31 | 0. 63374E-04 | 0. 38902E-06 | 0. 34313E+02 -0. 90074E+02 | 0. 10719E+03 | 0. 52381E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 17 | 0. 31 | 0. 14503E-03 | 0. 30074E-06 | 0. 35067E+02 -0. 11034E+03 | 0. 14369E+03 | 0. 69884E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 18 | 0. 32 | 0. 14503E-03 | 0. 30074E-06 | 0. 35067E+02 -0. 11034E+03 | 0. 14369E+03 | 0. 69884E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 19 | 0. 34 | 0. 59589E-04 | 0. 26184E-06 | 0. 34631E+02 -0. 10878E+02 | 0. 14149E+03 | 0. 68917E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 20 | 0. 37 | 0. 91125E-04 | 0. 26105E-06 | 0. 33504E+02 -0. 11034E+03 | 0. 14407E+03 | 0. 70110E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 21 | 0. 39 | 0. 21647E-03 | 0. 20172E-06 | 0. 33575E+02 -0. 11341E+03 | 0. 14878E+03 | 0. 72662E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 22 | 0. 41 | 0. 24074E-03 | 0. 20096E-06 | 0. 33596E+02 -0. 11298E+03 | 0. 14949E+03 | 0. 73022E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 23 | 0. 43 | 0. 15020E-03 | 0. 17971E-06 | 0. 33603E+02 -0. 11436E+03 | 0. 15048E+03 | 0. 73509E+02 | 0. 210E-01 | 0. 210E-01 | 0. 376E-01 |
| 0 | 24 | 0. 44 | 0. 19623E-03 | 0. 13847E-06 | 0. 33770E+02 -0. 12126E+03 | 0. 16097E+03 | 0. 78647E+02 | 0. 217E-01 | 0. 217E-01 | 0. 376E-01 |

ORIGINAL PAGE IS
OF POOR QUALITY

13726E-03 37860E-02 37821E+02
 13440E-02 37408E-02 37445E+02
 13288E-03 36895E-02 36866E+02
 13194E-03 36594E-02 36566E+02
 13114E-03 36294E-02 36268E+02
 13044E-03 35994E-02 35963E+02
 13000E-03 35694E-02 35663E+02
 12938E-03 35394E-02 35363E+02
 12876E-03 35094E-02 35063E+02
 12814E-03 34794E-02 34763E+02
 12752E-03 34494E-02 34463E+02
 12690E-03 34194E-02 34163E+02
 12628E-03 33894E-02 33863E+02
 12566E-03 33594E-02 33563E+02
 12504E-03 33294E-02 33263E+02
 12442E-03 32994E-02 32963E+02
 12380E-03 32694E-02 32663E+02
 12318E-03 32394E-02 32363E+02
 12256E-03 32094E-02 32063E+02
 12194E-03 31794E-02 31763E+02
 12132E-03 31494E-02 31463E+02
 12070E-03 31194E-02 31163E+02
 12008E-03 30894E-02 30863E+02
 11946E-03 30594E-02 30563E+02
 11884E-03 30294E-02 30263E+02
 11822E-03 30994E-02 30963E+02
 11760E-03 30694E-02 30663E+02
 11700E-03 30394E-02 30363E+02
 11638E-03 30094E-02 30063E+02
 11576E-03 29794E-02 29763E+02
 11514E-03 29494E-02 29463E+02
 11452E-03 29194E-02 29163E+02
 11390E-03 28894E-02 28863E+02
 11328E-03 28594E-02 28563E+02
 11266E-03 28294E-02 28263E+02
 11204E-03 27994E-02 27963E+02
 11142E-03 27694E-02 27663E+02
 11080E-03 27394E-02 27363E+02
 11018E-03 27094E-02 27063E+02
 10956E-03 26794E-02 26763E+02
 10894E-03 26494E-02 26463E+02
 10832E-03 26194E-02 26163E+02
 10770E-03 25894E-02 25863E+02
 10708E-03 25594E-02 25563E+02
 10646E-03 25294E-02 25263E+02
 10584E-03 24994E-02 24963E+02
 10522E-03 24694E-02 24663E+02
 10460E-03 24394E-02 24363E+02
 10400E-03 24094E-02 24063E+02
 10338E-03 23794E-02 23763E+02
 10276E-03 23494E-02 23463E+02
 10214E-03 23194E-02 23163E+02
 10152E-03 22894E-02 22863E+02
 10089E-03 22594E-02 22563E+02
 10027E-03 22294E-02 22263E+02
 9965E-03 21994E-02 21963E+02
 9902E-03 21694E-02 21663E+02
 9839E-03 21394E-02 21363E+02
 9776E-03 21094E-02 21063E+02
 9713E-03 20794E-02 20763E+02
 9650E-03 20494E-02 20463E+02
 9587E-03 20194E-02 20163E+02
 9524E-03 19894E-02 19863E+02
 9461E-03 19594E-02 19563E+02
 9400E-03 19294E-02 19263E+02
 9338E-03 18994E-02 18963E+02
 9276E-03 18694E-02 18663E+02
 9213E-03 18394E-02 18363E+02
 9151E-03 18094E-02 18063E+02
 9089E-03 17794E-02 17763E+02
 9026E-03 17494E-02 17463E+02
 8964E-03 17194E-02 17163E+02
 8901E-03 16894E-02 16863E+02
 8838E-03 16594E-02 16563E+02
 8775E-03 16294E-02 16263E+02
 8712E-03 15994E-02 15963E+02
 8649E-03 15694E-02 15663E+02
 8586E-03 15394E-02 15363E+02
 8523E-03 15094E-02 15063E+02
 8460E-03 14794E-02 14763E+02
 8397E-03 14494E-02 14463E+02
 8334E-03 14194E-02 14163E+02
 8271E-03 13894E-02 13863E+02
 8208E-03 13594E-02 13563E+02
 8145E-03 13294E-02 13263E+02
 8082E-03 12994E-02 12963E+02
 8019E-03 12694E-02 12663E+02
 7956E-03 12394E-02 12363E+02
 7893E-03 12094E-02 12063E+02
 7830E-03 11794E-02 11763E+02
 7767E-03 11494E-02 11463E+02
 7704E-03 11194E-02 11163E+02
 7641E-03 10894E-02 10863E+02
 7578E-03 10594E-02 10563E+02
 7515E-03 10294E-02 10263E+02
 7452E-03 9994E-02 9963E+02
 7389E-03 9694E-02 9663E+02
 7326E-03 9394E-02 9363E+02
 7263E-03 9094E-02 9063E+02
 7200E-03 8794E-02 8763E+02
 7137E-03 8494E-02 8463E+02
 7074E-03 8194E-02 8163E+02
 7011E-03 7894E-02 7863E+02
 6948E-03 7594E-02 7563E+02
 6885E-03 7294E-02 7263E+02
 6822E-03 6994E-02 6963E+02
 6759E-03 6694E-02 6663E+02
 6696E-03 6394E-02 6363E+02
 6633E-03 6094E-02 6063E+02
 6570E-03 5794E-02 5763E+02
 6507E-03 5494E-02 5463E+02
 6444E-03 5194E-02 5163E+02
 6381E-03 4894E-02 4863E+02
 6318E-03 4594E-02 4563E+02
 6255E-03 4294E-02 4263E+02
 6192E-03 3994E-02 3963E+02
 6129E-03 3694E-02 3663E+02
 6066E-03 3394E-02 3363E+02
 6003E-03 3094E-02 3063E+02
 5940E-03 2794E-02 2763E+02
 5877E-03 2494E-02 2463E+02
 5814E-03 2194E-02 2163E+02
 5751E-03 1894E-02 1863E+02
 5688E-03 1594E-02 1563E+02
 5625E-03 1294E-02 1263E+02
 5562E-03 994E-02 963E+02
 5499E-03 694E-02 663E+02
 5436E-03 394E-02 363E+02
 5373E-03 0. 3819E-02 0. 363E+02
 5310E-03 0. 3866E-02 0. 373E+02
 5247E-03 0. 3913E-02 0. 383E+02
 5184E-03 0. 3960E-02 0. 393E+02
 5121E-03 0. 4007E-02 0. 403E+02
 5058E-03 0. 4054E-02 0. 406E+02
 5000E-03 0. 4101E-02 0. 410E+02
 4947E-03 0. 4148E-02 0. 414E+02
 4884E-03 0. 4195E-02 0. 419E+02
 4821E-03 0. 4242E-02 0. 424E+02
 4758E-03 0. 4289E-02 0. 428E+02
 4695E-03 0. 4336E-02 0. 433E+02
 4632E-03 0. 4383E-02 0. 438E+02
 4569E-03 0. 4430E-02 0. 443E+02
 4506E-03 0. 4477E-02 0. 447E+02
 4443E-03 0. 4524E-02 0. 452E+02
 4380E-03 0. 4571E-02 0. 457E+02
 4317E-03 0. 4618E-02 0. 461E+02
 4254E-03 0. 4665E-02 0. 466E+02
 4191E-03 0. 4712E-02 0. 471E+02
 4128E-03 0. 4759E-02 0. 475E+02
 4065E-03 0. 4806E-02 0. 480E+02
 4002E-03 0. 4853E-02 0. 485E+02
 3939E-03 0. 4890E-02 0. 489E+02
 3876E-03 0. 4937E-02 0. 493E+02
 3813E-03 0. 4974E-02 0. 497E+02
 3750E-03 0. 5011E-02 0. 501E+02
 3687E-03 0. 5048E-02 0. 504E+02
 3624E-03 0. 5085E-02 0. 508E+02
 3561E-03 0. 5122E-02 0. 512E+02
 3498E-03 0. 5159E-02 0. 515E+02
 3435E-03 0. 5196E-02 0. 519E+02
 3372E-03 0. 5233E-02 0. 523E+02
 3309E-03 0. 5270E-02 0. 527E+02
 3246E-03 0. 5307E-02 0. 530E+02
 3183E-03 0. 5344E-02 0. 534E+02
 3120E-03 0. 5381E-02 0. 538E+02
 3057E-03 0. 5418E-02 0. 541E+02
 3000E-03 0. 5455E-02 0. 545E+02
 2937E-03 0. 5492E-02 0. 549E+02
 2874E-03 0. 5529E-02 0. 552E+02
 2811E-03 0. 5566E-02 0. 556E+02
 2748E-03 0. 5603E-02 0. 560E+02
 2685E-03 0. 5640E-02 0. 564E+02
 2622E-03 0. 5677E-02 0. 567E+02
 2559E-03 0. 5714E-02 0. 571E+02
 2496E-03 0. 5751E-02 0. 575E+02
 2433E-03 0. 5788E-02 0. 578E+02
 2370E-03 0. 5825E-02 0. 582E+02
 2307E-03 0. 5862E-02 0. 586E+02
 2244E-03 0. 5900E-02 0. 590E+02
 2181E-03 0. 5937E-02 0. 593E+02
 2118E-03 0. 5974E-02 0. 597E+02
 2055E-03 0. 6011E-02 0. 601E+02
 1992E-03 0. 6048E-02 0. 604E+02
 1929E-03 0. 6085E-02 0. 608E+02
 1866E-03 0. 6122E-02 0. 612E+02
 1803E-03 0. 6159E-02 0. 615E+02
 1740E-03 0. 6196E-02 0. 619E+02
 1677E-03 0. 6233E-02 0. 623E+02
 1614E-03 0. 6270E-02 0. 627E+02
 1551E-03 0. 6307E-02 0. 630E+02
 1488E-03 0. 6344E-02 0. 634E+02
 1425E-03 0. 6381E-02 0. 638E+02
 1362E-03 0. 6418E-02 0. 641E+02
 1300E-03 0. 6455E-02 0. 645E+02
 1237E-03 0. 6492E-02 0. 649E+02
 1174E-03 0. 6529E-02 0. 652E+02
 1111E-03 0. 6566E-02 0. 656E+02
 1048E-03 0. 6603E-02 0. 660E+02
 985E-03 0. 6640E-02 0. 664E+02
 922E-03 0. 6677E-02 0. 667E+02
 859E-03 0. 6714E-02 0. 671E+02
 796E-03 0. 6751E-02 0. 675E+02
 733E-03 0. 6788E-02 0. 678E+02
 670E-03 0. 6825E-02 0. 682E+02
 607E-03 0. 6862E-02 0. 686E+02
 544E-03 0. 6900E-02 0. 690E+02
 481E-03 0. 6937E-02 0. 693E+02
 418E-03 0. 6974E-02 0. 697E+02
 355E-03 0. 7011E-02 0. 701E+02
 292E-03 0. 7048E-02 0. 704E+02
 229E-03 0. 7085E-02 0. 708E+02
 166E-03 0. 7122E-02 0. 712E+02
 103E-03 0. 7159E-02 0. 715E+02
 40E-03 0. 7196E-02 0. 719E+02
 77E-03 0. 7233E-02 0. 723E+02
 114E-03 0. 7270E-02 0. 727E+02
 151E-03 0. 7307E-02 0. 730E+02
 188E-03 0. 7344E-02 0. 734E+02
 225E-03 0. 7381E-02 0. 738E+02
 262E-03 0. 7418E-02 0. 741E+02
 299E-03 0. 7455E-02 0. 745E+02
 336E-03 0. 7492E-02 0. 749E+02
 373E-03 0. 7529E-02 0. 752E+02
 410E-03 0. 7566E-02 0. 756E+02
 447E-03 0. 7603E-02 0. 760E+02
 484E-03 0. 7640E-02 0. 764E+02
 521E-03 0. 7677E-02 0. 767E+02
 558E-03 0. 7714E-02 0. 771E+02
 595E-03 0. 7751E-02 0. 775E+02
 632E-03 0. 7788E-02 0. 778E+02
 669E-03 0. 7825E-02 0. 782E+02
 706E-03 0. 7862E-02 0. 786E+02
 743E-03 0. 7900E-02 0. 790E+02
 779E-03 0. 7937E-02 0. 793E+02
 816E-03 0. 7974E-02 0. 797E+02
 853E-03 0. 8011E-02 0. 801E+02
 889E-03 0. 8048E-02 0. 804E+02
 926E-03 0. 8085E-02 0. 808E+02
 963E-03 0. 8122E-02 0. 812E+02
 1000E-03 0. 8159E-02 0. 815E+02
 1037E-03 0. 8196E-02 0. 819E+02
 1074E-03 0. 8233E-02 0. 823E+02
 1111E-03 0. 8270E-02 0. 827E+02
 1148E-03 0. 8307E-02 0. 830E+02
 1185E-03 0. 8344E-02 0. 834E+02
 1222E-03 0. 8381E-02 0. 838E+02
 1259E-03 0. 8418E-02 0. 841E+02
 1296E-03 0. 8455E-02 0. 845E+02
 1333E-03 0. 8492E-02 0. 849E+02
 1370E-03 0. 8529E-02 0. 852E+02
 1407E-03 0. 8566E-02 0. 856E+02
 1444E-03 0. 8603E-02 0. 860E+02
 1481E-03 0. 8640E-02 0. 864E+02
 1518E-03 0. 8677E-02 0. 867E+02
 1555E-03 0. 8714E-02 0. 871E+02
 1592E-03 0. 8751E-02 0. 875E+02
 1629E-03 0. 8788E-02 0. 878E+02
 1666E-03 0. 8825E-02 0. 882E+02
 1703E-03 0. 8862E-02 0. 886E+02
 1740E-03 0. 8900E-02 0. 890E+02
 1777E-03 0. 8937E-02 0. 893E+02
 1814E-03 0. 8974E-02 0. 897E+02
 1851E-03 0. 9011E-02 0. 901E+02
 1888E-03 0. 9048E-02 0. 904E+02
 1925E-03 0. 9085E-02 0. 908E+02
 1962E-03 0. 9122E-02 0. 912E+02
 2000E-03 0. 9159E-02 0. 915E+02
 2037E-03 0. 9196E-02 0. 919E+02
 2074E-03 0. 9233E-02 0. 923E+02
 2111E-03 0. 9270E-02 0. 927E+02
 2148E-03 0. 9307E-02 0. 930E+02
 2185E-03 0. 9344E-02 0. 934E+02
 2222E-03 0. 9381E-02 0. 938E+02
 2259E-03 0. 9418E-02 0. 941E+02
 2296E-03 0. 9455E-02 0. 945E+02
 2333E-03 0. 9492E-02 0. 949E+02
 2370E-03 0. 9529E-02 0. 952E+02
 2407E-03 0. 9566E-02 0. 956E+02
 2444E-03 0. 9603E-02 0. 960E+02
 2481E-03 0. 9640E-02 0. 964E+02
 2518E-03 0. 9677E-02 0. 967E+02
 2555E-03 0. 9714E-02 0. 971E+02
 2592E-03 0. 9751E-02 0. 975E+02
 2629E-03 0. 9788E-02 0. 978E+02
 2666E-03 0. 9825E-02 0. 982E+02
 2703E-03 0. 9862E-02 0. 986E+02
 2740E-03 0. 9900E-02 0. 990E+02
 2777E-03 0. 9937E-02 0. 993E+02
 2814E-03 0. 9974E-02 0. 997E+02
 2851E-03 0. 9999E-02 0. 999E+02
 2888E-03 0. 9999E-02 0. 999E+02
 2925E-03 0. 9999E-02 0. 999E+02
 2962E-03 0. 9999E-02 0. 999E+02
 3000E-03 0. 9999E-02 0. 999E+02
 3037E-03 0. 9999E-02 0. 999E+02
 3074E-03 0. 9999E-02 0. 999E+02
 3111E-03 0. 9999E-02 0. 999E+02
 3148E-03 0. 9999E-02 0. 999E+02
 3185E-03 0. 9999E-02 0. 999E+02
 3222E-03 0. 9999E-02 0. 999E+02
 3259E-03 0. 9999E-02 0. 999E+02
 3296E-03 0. 9999E-02 0. 999E+02
 3333E-03 0. 9999E-02 0. 999E+02
 3370E-03 0. 9999E-02 0. 999E+02
 3407E-03 0. 9999E-02 0. 999E+02
 3444E-03 0. 9999E-02 0. 999E+02
 3481E-03 0. 9999E-02 0. 999E+02
 3518E-03 0. 9999E-02 0. 999E+02
 3555E-03 0. 9999E-02 0. 999E+02
 3592E-03 0. 9999E-02 0. 999E+02
 3629E-03 0. 9999E-02 0. 999E+02
 3666E-03 0. 9999E-02 0. 999E+02
 3703E-03 0. 9999E-02 0. 999E+02
 3740E-03 0. 9999E-02 0. 999E+02
 3777E-03 0. 9999E-02 0. 999E+02
 3814E-03 0. 9999E-02 0. 999E+02
 3851E-03 0. 9999E-02 0. 999E+02
 3888E-03 0. 9999E-02 0. 999E+02
 3925E-03 0. 9999E-02 0. 999E+02
 3962E-03 0. 9999E-02 0. 999E+02
 4000E-03 0. 9999E-02 0. 999E+02
 4037E-03 0. 9999E-02 0. 999E+02
 4074E-03 0. 9999E-02 0. 999E+02
 4111E-03 0. 9999E-02 0. 999E+02
 4148E-03 0. 9999E-02 0. 999E+02
 4185E-03 0. 9999E-02 0. 999E+02
 4222E-

ORIGINAL PAGE IS
OF POOR QUALITY

File DBAO: CJPLOT1.CPR1 (359-204-0) last revised on 23-NOV-1988 11:20, is a 2 block sequential file owned by UIC CII,111. The records are variable length with FORTRAN (FTN) carriage control. The longest record is 25 bytes.
Job_PLOT1 (683) queued to SYSSESPPRTE on 23-NOV-1988 11:20-64 user NETNENPRIV-UHG-CII-111--under account 2010ADD at priority 100.
Started on printer _TF7 on 23-NOV-1988 11:20 from queue

ORIGINAL PAGE IS
OF POOR QUALITY

This ASCII art piece depicts a landscape scene with various elements. In the upper left, a cluster of tall trees is shown with vertical 'I' characters representing trunks and horizontal 'T' characters for branches. To the right of the trees is a large, dark, jagged mountain peak composed of 'X' and 'Z' characters. In the center, there's a wide expanse of water represented by a grid of '8' characters. The lower portion of the image features a dense forest of trees with 'P' and 'R' characters as trunks and 'K' characters for leaves. A small stream or path is indicated by a series of 'L' and 'J' characters winding through the trees at the bottom. The overall composition is a detailed landscape scene using a variety of characters to create different textures and shapes.

FILE DBAO:CPFL02.CPFL1 (363;197.0), last revised on 23-NOV-1988 11:21, is a 2 block sequential file owned by UIC CII,111. The records are variable length with FORTRAN (FTN) carriage control. The longest record is 25 bytes. JOB FL02 (see) queued to SPSSPRINT on 23-NOV-1988 11:21 by user NETCOPRIV, UIC CII,111, under account 2010000 at priority 100, started on printer JTF6 on 23-NOV-1988 11:21 #100 queue 4776.

(E12. 4, IX, E12. 4)
0. 3723E+01 0. 0000E+00
0. 3717E+01 0. 3801E-02
0. 6113E+01 0. 1878E-01
0. 6311E+01 0. 2763E-01
0. 6506E+01 0. 1267E+00
0. 6702E+01 0. 2208E+00
0. 6875E+01 0. 3257E+00
0. 7094E+01 0. 4269E+00
0. 7289E+01 0. 3217E+00
0. 7485E+01 0. 6038E+00
0. 7681E+01 0. 6756E+00
0. 7876E+01 0. 7379E+00
0. 8072E+01 0. 7781E+00
0. 8268E+01 0. 8511E+00
0. 8464E+01 0. 8772E+00
0. 8659E+01 0. 9371E+00
0. 8855E+01 0. 9687E+00
0. 9051E+01 0. 9874E+00
0. 9246E+01 0. 9763E+00
0. 9442E+01 0. 9773E+00
0. 9638E+01 0. 1000E+01

9.0 APPENDIX D

IMSL SUBROUTINE CALLS FROM RANDOM3 AND RANDOM4

RANDOM3

1. RNSET - Initializes a random seed for use in the IMSL random number generators.
2. RNNOR - Generates pseudorandom numbers from a standard normal distribution using an inverse CDF method.
3. RNLNL - Generates pseudorandom numbers from a lognormal distribution.
4. DESPL - Performs nonparametric probability density function estimation by the penalized likelihood method.
5. GCDF - Evaluates a general continuous cumulative distribution function given the ordinates of the density.

RANDOM4

1. RNSET - Initializes a random seed for use in the IMSL random number generators.
2. RNNOR - Generates pseudorandom numbers from a standard normal distribution using an inverse CDF method.
3. RNLNL - Generates pseudorandom numbers from a lognormal distribution.

10.0 APPENDIX E

SAMPLE SAS/GRAFH PROGRAM FOR RANDOM3 AND RANDOM4

```
data a;
INFILE 'PLOT1.CPR' FIRSTOBS=2;input x y;
GOPTIONS DEVICE=HP7470;
proc gplot;
axis1 label=(h=1 f=simplex 'LOG OF CYCLES')
      value=(h=1 f=simplex);
axis2 value=(h=1 f=simplex) label=none;
plot y*x / haxis=axis1 vaxis=axis2;
TITLE H=1 A=90 F=SIMPLEX 'PROBABILITY DENSITY FUNCTION';
symbol i=spline v=square;
data B;
INFILE 'PLOT2.CPR' FIRSTOBS=2;input x y;
proc gplot;
axis1 label=(h=1 f=simplex 'LOG OF CYCLES')
      value=(h=1 f=simplex);
axis2 value=(h=1 f=simplex) label=none;
plot y*x / haxis=axis1 vaxis=axis2;
TITLE H=1 A=90 F=SIMPLEX 'CUMULATIVE DISTRIBUTION FUNCTION';
symbol i=spline v=square;
```